




**XV ICFA Instrumentation School** 

Tata Institute of Fundamental Research, Mumbai

The school provides a foundation in instrumentation in particle physics, and the role instrumentation plays in experiments to advance the field. The scientific program will integrate academic courses and state-of-art laboratory sessions by experts in detector R&D. In the laboratory courses students will work in small groups to execute selected experimental techniques. In addition to talks on well established technologies, several talks will be dedicated to new technologies and to applications in other branches of science. Lecture courses and hands-on experiments will be integral parts of the school.









# From (very) Basic Ideas to Rather **Complex Gaseous Detector Systems**















Maxim Titov, CEA Saclay, Irfu, France





Online applications are invited from Ph.D. students in experimental HEP, who are in the early phase of their research career along with two recommendation letters.

Last Date for Application: 31st October, 2022





Standard Model Physcis

Physics at B-factories

Accelerator Physics

Gaseous detector

Gravitational Wave Detion, LIGO

Electronics, Triggers and DAQ

Didier Contardo (CNRS, France)

Honobo Zhu (IHEP China)

Neutrino Physics

LHC Physics

History of high energy physics in India / Asia

Astro-particle physics including Cosmic Ray

International Organizing Committee

Ian Shipsey, Chair (University of Oxford, UK)

Gerardo Herrera Corral (CINVESTAV, Maxic Peter Krizon (ISI, Slovenia) Gobinda Majumder (TIFR) India) Fabrice Retiere (TRIUMF, Canada







More information at https://www.tifr.res.in/~icfa2023/

Contact : icfa2023@tifr.res.in

Local Organizing Committee


Kajari Mazumdar (TIFR, Mumbai)

Gobinda Majumder, School Director (TIFR, Mumbai)



XI ICFA Instrumentation School, Tata Institute of Fundamental Research, Mumbai, India, Feb. 12-25, 2023

### To make a collider experiment, one needs:




A theory:





and a cafeteria



Clear and easy understandable drawings






Easy
access
to the
experiment



Physicists to operate detector/analyze data




and a Nobel prize




We will just concentrate on Particle Detectors – "Gaseous Detectors"

# **Gas-Based Detectors: A Brief History**



# Family of Gaseous Detectors with a Glorious Tradition

1908: FIRST WIRE COUNTER USED BY RUTHERFORD IN THE STUDY OF NATURAL RADIOACTIVITY






-

Nobel Prize in Chemistry in 1908

1968: MULTIWIRE PROPORTIONAL CHAMBER






Nobel Prize in Physics 1992


# 1928: GEIGER COUNTER SINGLE ELECTRON SENSITIVITY

E. Rutherford and H. Geiger, Proc.

Royal Soc. A81 (1908) 141



H. Geiger and W. Müller, Phys. Zeits. 29 (1928) 839





Walther Bothe Nobel Prize in Physics 1954 for the "coincidence method"



G. Charpak, Proc. Int. Symp. Nuclear Electronics (Versailles 10-13 Sept 1968)


### 1968: MWPC - Revolutionising the Way Particle Physics is Done



Before MWPC: Detecting particles was a mainly a manual, tedious and labour intensive job – unsuited for rare particle decays

1968: George Charpak developed the MultiWire Proportional Chamber, (MWPC), which revolutionized particle detection & HEP, and marked transition from Manual to Electronics era






"Image" & "Logic (electronics)" tradition combined into the "Electronics Image" detectors during the 1970ies

#### **Multi-Wire Proportional Chambers – Particle Physics Spin-Off**

Biospace: Company Founded In 1989 by Georges Charpak




#### http://www.biospacelab.com:


Our digital autoradiography system leverages the gas detection technology invented by our founder Georges Charpak:

Nobel Prize in Physics in 1992.

~ 2000: LOW-DOSE 3D IMAGING


# COMMERCIAL AUTORADIOGRAPHY SYSTEMS WITH GASEOUS DETECTORS







# **Georges Charpak with Friends**



### 1983/1984: Discovery of W and Z Bosons at UA1/UA2


UA1 used the largest wire / drift chamber of its day (5.8 m long, 2.3 m in diameter)

It can now be seen in the CERN Microcosm Exhibition

Discovery of W and Z bosons

C. Rubbia & S. Van der Meer,

1984:




# Time Projection Chamber (TPC) in Particle and Ion Physics

PEP4 (SLAC)



- ✓ Invented by David Nygren (Berkeley) in 1974
- Proposed as a central tracking device for the PEP-4 detector
   @ SLAC 1976
- More (and even larger) were built, based on MPWC readout
- New generation of TPCs use MPGD-based readout: e.g.
   ALICE Upgrade, T2K, ILC, CepC


An ultimate drift chamber design is TPC concept - 3D precision tracking with low material budget & enables particle identification through differential energy loss dE/dx measurement or cluster counting dN<sub>cl</sub>/dx techniques.




**TOPAZ (KEK)** 



**ALEPH (CERN)** 




STAR (LBL)



**DELPHI (CERN)** 






# Gaseous Detectors: From Wire/Drift Chamber → Time Projection Chamber (TPC) → Micro-Pattern Gas Detectors

Primary choice for large-area coverage with low material-budget (+ dE/dx measurement)

1990's: Industrial advances in photolithography has favoured the invention of novel microstructured gas amplification devices (MSGC, GEM, Micromegas, ...)



HL-LHC Upgrades: Tracking (ALICE TPC/MPGD); Muon Systems: RPC, CSC, MDT, TGC, GEM, Micromegas;

Future Hadron Colliders: FCC-hh Muon System (MPGD - OK, rates are comparable with HL-LHC)


Future Lepton Colliders: Tracking (FCC-ee / CepC - Drift Chambers; ILC / CePC - TPC with MPGD readout)

Calorimetry (ILC, CepC – RPC or MPGD), Muon Systems (OK)

Future Election-Ion Collider: Tracking (GEM, μWELL; TPC/MPGD), RICH (THGEM), TRD (GEM)

#### **CERN-RD51 Collaboration & MPGD Technology Advances**

RD51 CERN-based <u>"TECHNOLOGY - DRIVEN R&D COLLABORATION"</u> was established to advance MPGD concepts and associated electronics readout systems



- Renewed by the CERN Research Board for the 3<sup>rd</sup> term 2019 2023
- Beyond 2023, RD51 will serve as a nuclei of the new DRD1 ("all gas detectors")
  collaboration, anchored at CERN, as part of the ECFA Detector R&D Roadmap
  implementation

# 2014: RD51 Collaboration Meeting in Kolkata

# International

#### Workshop on Advanced Detectors IWAD

& 14th RD51 Collaboration Meeting

October 27 - 31, 2014 | Sponsor

Kolkata Board of Research in Nuclear Science India Department of Atomic Energy

Advanced gaseous detectors play a major role in modern day particle physics experiments. As spinoff they also find wide range of applications in the areas of medical imaging, radiography among others. In this regard a two-day International Workshop on Advanced Detectors (IWAD) is being organized during 27-28 October 2014 at VECC-SINP campus, Kolkata, INDIA. The workshop would be followed by 14th RD51 collaboration meeting at the same venue.

Local	Organizing	Committee	
Sudhee	R. Banerjee		VEC

Form or Burnering commit	
Sudhee R. Banerjee	VECC
Subhasis Chattopadhyay	VECC
(Chairman)	
Sukalyan Chattopadhyay	SINF
Supriya Das	Bi
Anand K. Dubey	VECC
(Convener)	
Nayana Majumdar	SINF
Supratik Mukhopadhyay	SINF
(Co-Chairman)	
Tapan K. Nayak	VECC
Lalit M. Pant	BARC

SINP

#### Satvaiit Saha Vikas Singhal Contact

E-mail : rd51india@vecc.gov.in Postal : Anand Kumar Dubey, Convener Variable Energy Cyclotron Center (VECC)
Department of Atomic Energy
1/AF, Bidhan Nagar, Kolkata - 700064, India Phone: +91 33 2318 2416 / 2410 Fax: +91 33 2334 6871

#### Areas to be covered in the workshop

27 - 28 October, 2014

Micropattern Gas Detectors (MPGD)

Resistive Plate Chambers

Applications of advanced detectors in **High Energy Physics** 

Medical and other applications of advanced detectors

#### International Advisory Committee

Amos Breskin Sunanda Banerjee SINP, India Giovanni Rencivenni INF-INFN Italy IUAC. India Rakesh K. Bhandari Sudeb Bhattacharya SINP, India Bikas K. Chakraborty SINP, India Paul Colas CEA/IRFU Saclay, France Vivek M. Datar NPD, BARC, India Klaus Desch Bonn University, Germany CEA Saclay, France Ioannis Giomataris Harry van der Graaf NIKHEF, The Netherlands Naba K. Mondal TIFR, India Sibaji Raha Bose Institute, India Leszek Ropelewski CERN Switzerland Fabio Sauli CERN Switzerland Christian J. Schmidt GSI Darmstadt, Germany Amar Sinha BARC, India Dinesh K. Srivastav VECC, India CERN, Switzerland Hans Taureg Maxim Titoy CEA Saclay, France Silvia Dalla Torre Trieste Univ. & INFN, Italy Yogendra P. Viyogi VECC, India Andy White Univ. of Texas, Arlington, USA

#### For participation in IWAD please send one page

abstract to rd51india@vecc.gov.in on or before















# CERN Courier (5 pages) Volume, October 2015

RN Courier October 2015

etector R&D

# RD51 and the rise of micro-pattern gas detectors

Since its foundation, the RD51 collaboration has provided important stimulus for the development of MPGDs.

Improvements in detector technology often come from capitalizing on industrial progress. Over the past two decades, advances in photolithography, microelectronics and printed circuits have opened the way for the production of micro-structured gas-amplification devices. By 2008, interest in the development and use of the novel micro-pattern gaseous detector (MPGD) technologies led to the

establishment at CERN of the RD51 collaboration of ated for a five-year term, RD51 was later payears beyond 2013. While many of the Mintroduced before RD51 was founded (figuriques becoming available or affordable, new still being introduced, and existing ones are still being introduced.

In the late 1980s, the development of the noter (MSGC) created great interest because capability, which was orders of magnitude chambers, and its position resolution of a few tens of micrometres at particle fluxes exceeding about 1 MHz/mm². Developed for projects at high-luminosity colliders, MSGCs promised to fill a gap between the high-performance but expensive solid-state detectors, and cheap but rate-limited traditional wire chambers. However, detailed studies of their long-term behaviour at high rates and in hadron beams revealed two possible weaknesses of the MSGC technology: the formation of deposits on the electrodes, affecting gain and performance ("ageing effects"), and spark-induced damage to electrodes in the presence of highly ionizing particles.

These initial ideas have since led to more robust MPGD structures, in general using modern photolithographic processes on thin insulating supports. In particular, ease of manufacturing, operational stability and superior performances for charged-particle tracking, muon detection and triggering have given rise to two main designs: the gas electron-multiplier (GEM) and the micromesh gaseous structure (Micromegas). By using a pitch size of a few hundred micrometres, both devices exhibit intrinsic high-rate capability (> 1 MHz/mm²), excellent spatial and multi-track resolution (around 30 µm and 500 µm, respectively), and time resolution for single photoelectrons in the sub-nanosecond range.

Coupling the microelectronics industry and advanced PCB technology has been important for the development of gas detectors with increasingly smaller pitch size. An elegant example is the use of a CMOS pixel ASIC, assembled directly below the GEM or Micromegas amplification structure. Modern "wafer post-processing technology" allows for the integration of a Micromegas grid directly on top of a Medipix or Timepix chip, thus forming



Fig.1. The seven working groups of RD51, with illustrations of just a few examples of the different kinds of work involved. Top left: the 20-year pre-history of RD51. (Image credits: RD51 Collaboration.)

integrated read-out of a gaseous detector (InGrid). Using this approach, MPGD-based detectors can reach the level of integraactness and resolving power typical of solid-state pixel rapplications requiring imaging detectors with largege and moderate spatial resolution (e.g. ring-imaging RICH) counters), coarser macro-patterned structures resting economic solution with relatively low mass struction – thanks to the intrinsic robustness of the less. Such detectors are the thick GEM (THGEM), multiplier (LEM), patterned resistive thick GEM)

(RETGEM) and the resistive-plate WELL (RPWELL).

#### RD51 and its working groups

The main objective of RD51 is to advance the technological development and application of MPGDs. While a number of activities have emerged related to the LHC upgrade, most importantly, RD51 serves as an access point to MPGD "know-how" for the worldwide community – a platform for sharing information, results and experience – and optimizes the cost of R&D through the sharing of resources and the creation of common projects and infrastructure. All partners are already pursuing either basic- or application-oriented R&D involving MPGD concepts. Figure 1 shows the organization of seven Working Groups (WG) that cover all of the relevant aspects of MPGD-related R&D.

WG1 Technological Aspects and Development of New Detector Structures. The objectives of WG1 are to improve the performance of existing detector structures, optimize fabrication methods, and develop new multiplier geometries and techniques. One of the most prominent activities is the development of large-area GEM, Micromegas and THGEM detectors. Only one decade ago, the largest MPGDs were around 40 × 40 cm<sup>2</sup>, limited by existing tools and materials. A big step towards the industrial manufacturing of MPGDs with a size around a square metre came with new fabrication methods - the single-mask GEM, "bulk" Micromegas, and the novel Micromegas construction scheme with a "floating mesh". While in "bulk" Micromegas, the metallic mesh is integrated into the PCB read-out, in the "floating-mesh" scheme it is integrated in the panel containing drift electrodes and placed on pillars when the chamber is closed. The single-mask GEM technique overcomes the cumbersome practice of alignment of two masks between top and bottom films, which limits the achievable lateral size to 50 cm. This technology, together with the novel "self-stretching technique" for assembling GEMs without glue and spacers, simplifies the fabrication process to such an extent that, especially for large-volume production, the cost per unit area drops by orders of magnitude.

26


### 2022: MPGDs for High Luminosity LHC Upgrades

The <u>successful implementation of MPGDs for relevant upgrades of CERN</u> experiments indicates the degree of maturity of given detector technologies for constructing large-size detectors, the level of dissemination within the HEP community and their reliability














https://ep-news.web.cern.ch/content/atlas-new-small-wheel-upgrade-advances-0


https://ep-news.web.cern.ch/upgraded-alice-tpc

https://ep-news.web.cern.ch/content/demonstratingcapabilities-new-gem



# **Tracking Detectors: History and Trends**

- Cloud Chambers, Nuclear Emulsions + Geiger-Müller tubes
  - → dominated until the early 1950s: Cloud Chambers now very popular in public exhibitions related to particle physics
- Bubble Chambers had their peak time between 1960 and 1985
  - → last big bubble chamber was BEBC at CERN
- Since 1970s: Wire Chambers (MWPCs and drift chambers) started to dominate; recently being replaced by Micro-Pattern Gas Detectors (MPGD)
- Since late 1980s: Solid state detectors are in common use
  - → started as small sized vertex detectors (at LEP and SLC)
  - → now ~200 m<sup>2</sup> Si-surface in CMS tracker
  - Most recent trend: silicon strips & hybrid detectors, 3D-sensors, CMOS Monolithic Active Pixel Sensors (MAPS) → See Frank Hartmann lectures




# State-of-the-Art in Tracking and Vertex Detectors


**Today's 3 major technologies of Tracking Detectors:** 


#### Silicon (strips, pixels, 3D, CMOS, monolithic):

→ electron – hole pairs in solid state material



Fiber Trackers: → scintillation light detected with photon detectors (sensitive to single electrons)





LHCb Tracker Upgrade (Sci-fibers with SiPM readout):

#### Gaseous (MWPC, TPC, RPC, MPGDs):

→ ionization in gas



inst

Published by IOP Publishing for Sissa Medialab

RECEIVED: June 12, 2020 ACCEPTED: June 28, 2020 Published: October 22, 2020

INTERNATIONAL CONFERENCE ON INSTRUMENTATION FOR COLLIDING BEAM PHYSICS

Novosibirsk, Russia 24–28 February, 2020

M. Titov, JINST15 C10023 (2020)

Next frontiers in particle physics detectors: INSTR2020 summary and a look into the future

#### M. Titov

Commissariat à l'Énergie Atomique et Énergies Alternatives (CEA) Saclay, DRF/IRFU/DPHP, 91191 Gif sur Yvette Cedex, France

E-mail: maxim.titov@cea.fr


### **Gaseous Detectors: Working Principle**

- a charged particle passing through the gas ionizes a few gas molecules;
- ✓ the electric field in the gas volume transports the ionisation electrons and provokes multiplication;
- the movement of electrons and ions leads to induced currents in electrodes;
- the signals are processed and recorded.

#### Example:

- 10 GeV muon crossing
- Gas mixture: Ar/CO2 (80:20) %
- Electron are shown every 100 collisions, but have been tracked rigorously.
- lons are not shown.

#### At the 100 μm – 1 mm scale:





### Gas Detectors: Why Use Gas as a Medium for Ionization?


- ✓ Effectively quite light in terms of gm/cm², requirement for reducing multiple scattering in particle physics
- ✓ Few other technologies can easily realize detectors with as large a sensitive area as gas-filled devices
- √ Gas-filled detectors are relatively cheap in terms of \$ per unit area/volume
- ✓ There are optimized gas mixtures for charged particles detection (high energy and nuclear physics), X-rays (synchrotron physics, astronomy) and neutrons (neutron scattering, national security)
- ✓ Electron transport characteristics are favorable and well characterized.
- ✓ Gas gain, M (electron multiplication factor), can be achieved, over many orders of magnitude (large dynamic range)
- ✓ Ionization collection or fluorescence emission can form the signal


#### **Gaseous Detectors: Signal Generation**


- √ Ionization statistics in gas
- ✓ Charge transport in gas
  - a) Diffusion
  - b) Electron and ion mobility
  - c) Drift velocity
- ✓ Loss of Electrons / Attachment
- ✓ Charge multiplication /
  Gas Amplification


















Efficient Gaseous Detector development (energy deposit, electric fields, drift velocity & diffusion, attachment and amplification) is today possible with existing precise and reliable simulation tools

# Gaseous Detectors: Ionization Statistics (I)

#### **TOTAL IONIZATION:**

- Primary electron-ion pairs
  - → Coulomb interactions of charged particles with molecules
  - → typically ~ 30 primary ionization clusters /cm in gas at 1 bar
- Secondary ionization: clusters and delta-electrons → on average 90 electrons/cm in gas at 1 bar



The actual number of primary electron/ion pairs  $(n_p)$  is Poisson distributed:


$$P(n_p, \langle n_p \rangle) = \frac{\langle n_p \rangle^{n_p} e^{-\langle n_p \rangle}}{n_p!}$$

σ<sub>I</sub>: Ionization x-Sectionn<sub>e</sub>: Electron densityL: Thickness

$$\langle n_p \rangle = L/\lambda$$

 $\lambda = 1/(n_e \sigma_I)$ 

Number of primary electron/ion pairs in frequently used gases:



#### Detection efficiency of a perfect detector is limited to:

 $\rightarrow$  for thin (L) layers  $\varepsilon$  can be significantly lower than 1


$$\varepsilon = 1 - e^{-n_p}$$

$$\langle n_p \rangle = L/\lambda$$

GAS (STP)	thickness	E (%)
Helium	1 mm	45
	2 mm	70
Argon	1 mm	91.8
0	2 mm	99.3

# **Gaseous Detectors: Ionization Statistics (II)**





Relevant Parameters for gas detectors

Ionization energy : Average energy/ion pair :


Average number of primary ion pairs [per cm]

Average number of ion pairs [per cm]

Differences due to  $oldsymbol{\delta}$ -electrons  $egin{array}{c} \mathsf{E_i} & & & & & \\ \mathsf{W_i} & & & & & & \\ & & & & & & \\ \end{pmatrix}$ 


[about 2-6 times n<sub>p</sub>]
[L: layer thickness]

About 0:6% of released electrons in Ar have > 1keV energy > practical range is 70 um, contributing to coordinate meas. error



#### Total Ionization/Cluster Size Distribution:

Probabilities (%) to create N<sub>el</sub> electrons (electrons are not evenly spaced, not even exponentially):





less multi-electron clusters at Helium (better!)

# **Ionization Statistics: Importance of PAI Model**

- Every ionization process is a quantum mechanical transition initiated by the Coulomb field of the particle and the field created by neighbouring polarizable atoms; the average energy losses are described by the Bethe-Bloch formula with Sternheimer's density effect corrections;
- The fluctuations caused by Rutherford scattering on quasi-free electrons follow a Landau
  distribution and the influence of atomic shells is described by the photoabsorption ionization
  (PAI) model, which allows simulation of each energy transfer, with relaxation cascades and
  simulation of delta-electrons;
- Heed: a photo-absorption & ionization model:

Energy loss fluctuations 2 GeV protons on an (only!) 5 cm thick Ar gas layer:





- Importance of PAI model (all terms in formula are important):
  All electron orbitals (shells) participate:
  - → outer shells: frequent interactions, few electrons;
  - → inner shells: few interactions, many electrons.

#### **Ionization Statistics: Table for Most Common Gases**

**Table 35.1:** Properties of noble and molecular gases at normal temperature and pressure (NTP: 20° C, one atm).  $E_X$ ,  $E_I$ : first excitation, ionization energy;  $W_I$ : average energy for creation of ion pair;  $dE/dx|_{\min}$ ,  $N_P$ ,  $N_T$ : differential energy loss, primary and total number of electron-ion pairs per cm, for unit charge minimum ionizing particles. Values often differ, depending on the source, and those in the table should be taken only as approximate.

F. Sauli, M. Titov, Review of Particle Physics, Particle Data Group (2022)

Gas	Density,	$E_x$	$E_{I}$	$W_{I}$	$dE/dx _{\min}$	$N_P$	$N_T$
	$ m mgcm^{-3}$	eV	eV	eV	$ m keVcm^{-1}$	$\mathrm{cm}^{-1}$	$\mathrm{cm}^{-1}$
$\overline{\mathrm{H}_2}$	0.084	10.8	13.6	37	0.34	5.2	9.2
Не	0.179	19.8	24.6	41.3	0.32	3.5	8
Ne	0.839	16.7	21.6	37	1.45	13	40
Ar	1.66	11.6	15.7	26	2.53	25	97
Xe	5.495	8.4	12.1	22	6.87	41	312
$CH_4$	0.667	8.8	12.6	30	1.61	28	54
$C_2H_6$	1.26	8.2	11.5	26	2.91	48	112
$iC_4H_{10}$	2.49	6.5	10.6	26	5.67	90	220
$CO_2$	1.84	7.0	13.8	34	3.35	35	100
$CF_4$	3.78	10.0	16.0	35 - 52	6.38	52 - 63	120

Ar/CO<sub>2</sub> (70/30):

$$N_P = 25 \cdot 0.7 + 35 \cdot 0.3 = 28 \frac{pairs}{cm}; \qquad N_T = \frac{2530}{26} \cdot 0.7 + \frac{3350}{35} \cdot 0.3 \approx 97 \frac{pairs}{cm}.$$

N<sub>T</sub> ~ 100 e-ion pairs during ionization process (typical number for 1 cm of gas) is not easy to detect → typical noise of modern pixel ASICs is ~ 100e- (ENC)

Need to increase number of e-ion pairs → ... ⊗ ... how ??? → GAS AMPLIFICATION

# **Transport of Electrons in Gases: Drift Velocity**


Electron transport theory = BALANCE BETWEEN ENERGY ACQUIRED FROM THE FIELD AND COLLISION LOSSES

Electrons are completely 'randomized' in each collision. The actual drift velocity v along the electric field is quite different from the average velocity u of the electrons i.e.  $\rightarrow$  about 100 times smaller.


The velocities v and u are determined by the atomic cross section  $\sigma(\epsilon)$  and the fractional energy loss  $\Delta(\epsilon)$  per collision (N is the gas density i.e. number of gas atoms/m³, m is the electron mass.):


$$v = \sqrt{\frac{eE}{mN\sigma}}\sqrt{\frac{\Delta}{2}}$$

$$u = \sqrt{\frac{eE}{mN\sigma}\sqrt{\frac{2}{\Delta}}}$$




Because  $\sigma(\epsilon)$  und  $\Delta(\epsilon)$  show a strong dependence on the electron energy in the typical electric fields, the electron drift velocity v shows a strong and complex variation with the applied electric field.







# **Transport of Electrons in Gases: Drift Velocity**

#### CHARGE TRANSPORT DETERMINED BY ELECTRON-MOLECULE CROSS SECTION:



- $\triangleright$  CO<sub>2</sub> is linear:
  - ▶ O C O
- Vibration modes are numbered V(ijk)
  - i: symmetric,
  - j: bending,
  - k: anti-symmetric.





#### Magboltz: microscopic e transport

- ▶ A large number of cross sections for 60 molecules...
  - Numerous organic gases, additives, e.g. CO<sub>2</sub>:
    - elastic scattering,
    - 44 inelastic cross sections (5 vibrations and 30 rotations + super-elastic and 9 polyads),
    - attachment,
    - ▶ 6 excited states and
    - 3 ionisations.
  - ▶ noble gases (He, Ne, Ar, Kr, Xe):
    - elastic scattering,
    - ▶ 44 excited states and
    - 7 ionisations.

LXcat (pronounced *elecscat*) is an open-access website for collecting, displaying, and downloading ELECtron SCATtering cross sections and swarm parameters (mobility, diffusion coefficient, reaction rates, etc.) required for modeling low temperature plasmas. [...]"

#### Lxcat:

http://www.lxcat.laplace.univ-tlse.fr/]

#### Magboltz:


S. Biagi, Nucl. Instr. and Meth. A421 (1999) 234 http://magboltz.web.cern.ch/magboltz/

#### **Transport of Electrons in Gases: Drift Velocity**

Large drift velocities are achieved by adding polyatomic gases (usually hydrocarbons, CO2, CF4) having large inelastic component at moderate energies of a few eV → electron "cooling" into the energy range of the Ramsauer-Townsend minimum (at ~0.5 eV) of the elastic cross-section.


Large range of drift velocities in gases: 1 .... 10 cm/µs; typical categories:

- ✓ "slow" gases, e.g. Ar/CO2 mixtures
  1-2 cm/µs, almost linear
  dependence on E-field
- √ "fast" gases, e.g. Ar/CF4 mixtures
  ~10-15 cm/µs
- "saturated" gases, e.g. Ar/CH4; e.g. Ar/CH4 (90/10) – drift velocity less sensitive to E-field variations and nearly constant (useful for drift chamber operation)




Even small addition of CO2 to Ar makes gas dramatically fster

Additives like CO2 & hydrocarbons are called "quenchers" or "admixtures"




### **Selection of Gas Mixture: Quenching of Photons**

- Slight problem in gas avalance
  - → Argon atoms can be ionized but also can be brought into excited states
  - > Exited Argon atoms can only de-exite by emission of high-UV photons




consequence: UV photons
(>11.6 eV) hit surface
of metals (cathode)
and free new electrons,
ionization energy of Cu = 7.7 eV



VERY unstable operation

- Solution
- → Add gases with many vibrational and rotational energy levels: CO<sub>2</sub>, CH<sub>4</sub>
- → Absorption of UV photons over a wide energy range; dissipation by collisions or dissociation into smaller molecules (see aging effects)



### **Transport of Electrons in Gases: Diffusion**

An initially point like cloud of electrons will 'diffuse' because of multiple collisions and assume a Gaussian shape. The diffusion depends on the average energy of the electrons. The variance  $\sigma^2$  of the distribution grows linearly with time. In case of an applied electric field it grows linearly with the distance.

$$n(x) = \left(\frac{1}{\sqrt{4\pi Dt}}\right)^3 e^{\frac{-(x-v_D t)^2}{4Dt}}$$

$$v_{D} = \frac{\Delta s}{\Delta t} \qquad \sigma_{x} = \sqrt{2Dt} = \sqrt{2D\frac{s}{v_{D}}}$$


Solution of the diffusion equation (l=drift distance)

$$D = \frac{2}{3} \frac{v}{eE} \epsilon \qquad \qquad \sigma_x = \sqrt{\frac{4}{3} \frac{l}{eE} \epsilon}$$

'Cold' gases are close to the thermodynamic limit i.e. gases where the average microscopic energy  $\epsilon$ =1/2mu2 is close to the thermal energy 3/2kT.


CH<sub>4</sub> has very large fractional energy loss  $\rightarrow$  low  $\epsilon \rightarrow$  low diffusion.

Argon has small fractional energy loss/collision  $\rightarrow$  large  $\epsilon \rightarrow$  large diffusion.



#### **Transport of Electrons in Gases: Diffusion**

Electric field alters the diffusion so that it is necessary to introduce two diffusion coefficients: longitudinal diffusion ( $\sigma_L$ ) and transverse diffusion ( $\sigma_T$ )




CO₂ is much cooler gas than CH₄ at low electric fields → allows to optimize separately diffusion properties in the drift and multiplication regions (but, CH4 is much better quencher than CO2)


CF4 has the largest drift velocity

& lowest electron diffusion among known gases due to the sizeable Ramsauer-Townsend dip in the elastic cross-section which coincides with a very large vibrational modes (but, CF4 has a small quenching cross-section of excited Ar states

visible light)

and emits light from the far UV to the





#### **Electron Drift in Presence of Electric and Magnetic Fields**

Equation of motion of free charge carriers in presence of E and B fields:

$$m\frac{d\vec{v}}{dt} = e\vec{E} + e(\vec{v} \times \vec{B}) + \vec{Q}(t)$$
 where  $\vec{Q}(t)$  stochastic force resulting from collisions

Time averaged solutions with assumptions: 
$$\vec{v}_D = \langle \vec{v} \rangle = const.$$
  $\langle \vec{Q}(t) \rangle = \frac{m}{\tau} \vec{v}_D$  friction force

$$\left\langle \frac{d\vec{v}}{dt} \right\rangle = 0 = e\vec{E} + e(\vec{v}_D \times \vec{B}) - \frac{m}{\tau} \vec{v}_D$$
  $\tau$  mean time between collisions

$$\vec{v}_D = \frac{\mu |\vec{E}|}{1 + \omega^2 \tau^2} \left[ \hat{E} + \omega \tau (\hat{E} \times \hat{B}) + \omega^2 \tau^2 (\hat{E} \cdot \hat{B}) \hat{B} \right]$$

More precise calculation is available in Magboltz, which computes drift velocity by tracing electrons at the microscopic level through numerous collisions with gas molecules

$$\vec{E} \parallel \vec{B} \quad \sigma_L = \sigma_0 \quad \sigma_T = \frac{\sigma_0}{\sqrt{1 + \omega^2 \tau^2}}$$

E.g.:  $\omega \tau \sim 20$  for Ar/CF4/iC4H10 (95:3:2)


$$\mu = \frac{e\,\tau}{m}$$

mobility

$$\omega = \frac{eB}{m}$$

 $\omega = \frac{eB}{}$  cyclotron frequency

This reduction iis exploited to substantially improve spatial resolution in the Drift and TPC Chambers




#### **Electron Capture Losses for Electronegative Gases (Attachment)**

- ✓ Some quencher gases can attach electrons
- ✓ Energy-momentum conservation: 3-body or dissociation
- ✓ The attachment cross section is energy-dependent, therefore strongly depends on the gas composition and electric field


#### Examples:

- $\triangleright$  O<sub>2</sub>: mostly 3-body O<sub>2</sub> and at higher  $\epsilon$  2-body dissociative;
- H<sub>2</sub>O: [H<sub>2</sub>O]<sub>n</sub> has positive electron affinity, H<sub>2</sub>O probably not;
- $\triangleright$  CF<sub>4</sub>: mostly dissociative F<sup>-</sup> + CF<sub>3</sub>, F + CF<sub>3</sub><sup>-</sup> (below 10 eV);
- SF<sub>6</sub>: SF<sub>6</sub><sup>-\*</sup> < 0.1 eV,  $\sigma$ =10<sup>-18</sup> cm<sup>2</sup>, then F<sup>-</sup> + SF<sub>n</sub><sup>-</sup> (n=3, 4, 5)
- CS<sub>2</sub>: negative ion TPC;
- $\triangleright$  CO<sub>2</sub>: O<sup>-</sup>, [CO<sub>2</sub>]<sub>n</sub> but no CO<sub>2</sub> (4 eV and 8.2 eV).


# Certain quenchers as CO2 can significantly enhance the effect of oxygen → large uncrease in attachment



Attachmant coefficient of oxygen:



Electrons surviving after 20 cm drift (E = 200 V/cm):



#### **Transport of lons in Gases: Drift and Diffusion**

Signals in Wire Chambers, Micromegas are generated by ion movement

#### Drift velocity of ions

is almost linear function of E  $v_D^{ion} = \mu^{ion} E$ 

Mobility:

$$\mu^{ion} = \frac{e \, \tau}{m}$$
 is

constant for given gas at fixed P and T, direct consequence of the fact that average energy of ion is unchanged up to very high E fields.

#### Diffusion of ions

IONS DIFFUSION (Einstein's law):


$$\frac{D}{\mu} = \frac{KT}{e}$$


$$\sigma_x = \sqrt{2Dt}$$

$$\sigma_{x} = \sqrt{\frac{2KT}{e}} \frac{x}{E}$$

Linear diffusion is independent of the nature of ions and gas → thermal limit (same for all gases)

It has been historically assumed that, due to a very effective charge transfer mechanism, only ions with the lowest ionization potential survive after a short path in the mixture → NOT TRUE !!!





### **Transport of lons in Gases: Drift and Diffusion**

Recent experimental data suggests that the signal ions, in e.g. CO2-quenched mixtures of Ar and Ne are CO+2 • (CO2)n cluster ions, and not CO+2 or noble gas ions


#### Principal reactions involving CO<sub>2</sub>

- ► Ar<sup>+</sup>: charge exchange,  $\tau \approx 0.85$  ns
  - $Ar^+ + CO_2 \rightarrow Ar + CO_2^+$
- ▶ Ne<sup>+</sup>: charge transfer in 2-steps,  $\tau \approx 8$  ns
  - ightharpoonup Ne<sup>+</sup> + CO<sub>2</sub>  $\rightarrow$  Ne + CO<sup>+</sup> + O
  - $\triangleright$  CO<sup>+</sup> + CO<sub>2</sub>  $\rightarrow$  CO + CO<sub>2</sub><sup>+</sup>
- ► CO<sub>2</sub>: 3-body association, 7-20 ps
  - $\triangleright$  CO<sub>2</sub><sup>+</sup> + 2CO<sub>2</sub>  $\rightarrow$  CO<sub>2</sub><sup>+</sup>•CO<sub>2</sub> + CO<sub>2</sub>

#### Reaction dynamics in Ar CO<sub>2</sub>

- ► Reactions:
  - $\rightarrow$  Ar<sup>+</sup> + CO<sub>2</sub>  $\rightarrow$  Ar + CO<sub>2</sub><sup>+</sup>
  - CO<sub>2</sub><sup>+</sup> + 2CO<sub>2</sub> → CO<sub>2</sub><sup>+</sup>•CO<sub>2</sub> + CO<sub>2</sub>
  - $Ar^+ + 2Ar \rightarrow Ar^+ \cdot Ar + Ar$
- Parameters:
  - p = 1 bar
  - ▶ mix: 90 % Ar + 10 % CO,

R. Veenhof, private communications Y. Kalkan, JINST 10, 07, P07004 (2015)



#### Life cycle of $CO_2^+ \bullet (CO_2)_n$

- ► CO<sub>2</sub>+•CO<sub>2</sub> has a dissociation energy of 0.6 eV
  - ▶ far above thermal energies at 1 bar (35 meV);
  - it is a long-lived cluster calculated lifetime = 5 ns. [B.M. Smirnov, "Cluster Ions and Van Der Waals Molecules," CRC press]
- ► This is much longer than the formation time  $\tau = 7-20$  ps via 3-body association in 10 % CO<sub>2</sub> with Ar + CO<sub>2</sub> as "helpers".
- ▶ Hence, any isolated CO₂⁺ rapidly binds again.
- ▶  $CO_2^{+\bullet}(CO_2)_n$  probably lives shorter but will recombine. The cluster size n will therefore fluctuate at the ns time scale.

#### Summary ions

- Avalanches ionise the constituent gases, and the initial ions undergo a staggering sequence of reactions.
  - In Ar-CO₂ and Ne-CO₂ mixtures, the signal ions are CO₂+•(CO₂)₂ clusters, which are slower than CO₂+;
  - water forms larger clusters, further reducing the mobility;
  - ▶ pure noble gases form dimers, Ar<sub>2</sub><sup>+</sup>, Ne<sub>2</sub><sup>+</sup> which are faster than Ar<sup>+</sup> and Ne<sup>+</sup> due to resonant charge exchange;
  - Xe forms dimers, trimers and probably bigger objects;
  - alkanes combine to form heavier molecules.

Since the cluster ions are slower than the initial ions, the signals induced by ion motion in Micromegas or TPC might be altered (also lead to larger space-charge effect in gas vomule)

#### **Gaseous Detectors: Software and Simulation Tools**

Garfield, together with HEED, Degrad, Magboltz, SRIM, ANSYS, COMSOL, and neBEM software packages represent the core simulation tools for microscopic modelling of gaseous detector response

## Monte Carlo approach – a way out ?

- ► Analytic models are precious for the insight they afford.
- But the complexity of real gases and detectors make realistic models unwieldy:
  - inelastic collisions (vibrations, rotations, polyads);
  - excitations and Penning transfers;
  - ionisation:
  - attachment:
  - intricate, position-dependent E and B fields.
- Predictions for experiments are more practical using a Monte Carlo approach, here based on Magboltz.

- ✓ HEED energy loss, a photoabsorption and ionization model
- ✓ **DEGRAD** electron transport, cluster size distribution
- ✓ Magboltz electron transport properties: drift, diffusion, multiplication, attachment
- ✓ ANSYS, COMSOL, neBEM electric field maps in 2D / 3D
- ✓ Garfield fiedls, drift properties, signals (interfaced to above)

#### Some recent highlights:

- Garfield++ et al. (new development and maintenance of codes, documentation, examples)
- Garfield++ and delayed weighting fields in the calculation of the induced signal (resistive electrodes)
- Greenhouse gases
- Improving accuracy of the modelling and the detector physics understanding: Penning transfer, Non equilibrium effect in gaseous detectors, lons and cluster ions

## **Electric Fields: (nearly) Exact Boundary Element Method**

neBEM Field Solver (that solves the Poisson equation to obtain electric field throughout the device volume) is an integrated part of device simulation. One such Green function based solver (nearly exact Boundary Element Method), is integrated to GARFIELD since 2009.

#### Merits of neBEM:

- Analytic integration of influence of charge distributed over small rectangular / triangular boundary elements (new formulation). Very precise potential and electric field values are obtained for any 2D / 3D geometry.
- Competitively accurate w.r.t any other commercial FEM / BEM package.
- Primitive geometry modeling.
- Parallelized using OpenMP.
- Field maps and reduced order modeling crudely implemented.
- Preliminary implementation of space charge and charging up simulations.

RD51 Note-2009-001

RD51-NOTE-2009-001

NIMA, vol. 566, issue 2, p489

neBEM: a Field Solver

Supratik Mukhopadhyay, Nayana Majumdar, Sudeb Bhattacharya

INO Section, Saha Institute of Nuclear Physics 1/AF, Sector 1, Bidhannagar, Kolkata 700064, WB, India supratik.mukhopadhyay@saha.ac.in, nayana.majumdar@saha.ac.in, sudeb.bhattacharya@saha.ac.in

## http://nebem.web.cern.ch/nebem (Supratik Mukhopadhay, Nayana Majumdar)

Maintained and updated by SINP (independent release till 05 Mar 2019, version 1.9.04; Since 2019, released along with Garfield++)

#### Future projects for neBEM:

- Orders of magnitude improvement in speed is possible:
  - > FMM / GMRES or similar algorithms.
  - Better parallelization (OpenMP, GPU)
  - Smaller data storage and faster flow.
- Improvements in geometry modeler, surface mesh generation, adaptive mesh.
- Space charge and charging up simulation to be improved significantly. Charge transport through dielectrics is another important area to be explored.
- Graphical user interface.

## **Garfield ++ Package: Software Simulation and Tools**

Garfield++ Installation Examples Documentation

#### Garfield++

#### Heinrich Schindler, Rob Veenhof

#### About

Garfield++ is a toolkit for the detailed simulation of particle detectors based on ionisation measurement in gases and semiconductors. The main with the Garfield program. The main differences are the more up-to-date treatment of electron transport, the possibility to simulate silicon sense

More... Support of Garfield++ package (maintenance and new 1g ion tracks using tables computed with SRIM or the TRIM interface. developments)- a unique software package

- for microscopic modeling of small-scale structures
- Examples
- Documentation (User Guide, Doxygen, FAQ)


#### Support

- If you have any questions, please send a mail to garfield-support@cern.ch (or contact Heinrich Schindler or Rob Veenhof directly).
- To receive (infrequent) announcements about updates of the code, please subscribe to the mailing list garfield-users@cern.ch on E-Gr
- Issues can be reported on JIRA or GitLab.

#### Related calculations

Modelling of avalanches and streamers with COMSOL.

#### Gitlab Repository



#### Examples

#### **Tutorials**

#### First steps



- . Simulating a GEM: finite element model, microscopic tracking of electrons
- · Simulating a silicon sensor: user-parameterized fields, strip/pixel weighting fields, Monte Carlo integration of drift lines, signals
- . Simulating a Resistive Plate Chamber

#### Primary ionization

· Simulating charged-particle tracks using Heed.

- . Generating gas tables and dealing with gas files.

Transport properties

Penning transfer,
 Cross-sections used by Magboltz.

#### Electric fields

- . Importing finite-element field maps calculated using
  - Elmer and Gmsh.
  - ANSYS, for two-dimensional and three-dimensional problems,
  - COMSOL
  - · CST.
- Importing TCAD field maps.
- · Computation of electric fields using the nearly exact Boundary Element Method (neBEM).

#### Signals

· Weighting fields and induced currents

#### Applications

#### Micropattern gas detectors

· Movies of avalanches in a single GEM es of avalanches in a triple GEM

Sign in

ging up of a GEM on detection with a Thick GEM

energy pion detection with a Micromegas facing with Geant4


#### ambers

#### lation of the ALICE TPC

troluminescence

#### Gas properties

Paschen curves




## **Signal Formation in Detectors with Resistive Elements**


RD51 supports ongoing efforts on interfacing between different modeling tools – to address properly involved processes at the microscopic level - extending present simulation framework to other gaseous & Si-detectors

EP R&D SEMINAR, Signal formation in detectors with resistive elements by **Djunes Janssens:** 


https://indico.cern.ch/event/1167590/contributions/4903447/attachments/2460899/4219187/EPSeminar\_DjunesJanssens.pdf


Garfield++ and COMSOL to model the signal formation in detectors with resistive elements by applying an extended form of the Ramo-Shockley theorem





#### Solid State (Silicon, Diamond,..)





## Single Wire Proportional Counter: Avalanche Development

Thin anode wire (20 – 50 um) coaxial with cathode

gas cathode gas b anode


**Electric field:** 

$$E(r) = \frac{CV_0}{2\pi\varepsilon_0} \frac{1}{r}$$


$$C = \frac{2\pi\varepsilon_0}{\ln(b/a)}$$


- Strong increase of E-field close to the wire
  - → electron gains more and more energy
- Above some threshold (>10 kV/cm)
  - → electron energy high enough to ionize other gas molecules
  - → newly created electrons also start ionizing
- Avalanche effect: exponential increase of electrons (and ions)
- > Measurable signal on wire
  - → organic substances responsible for "quenching" (stopping) the discharge


Avalanche development in the high electric field around a thin wire (multiplication region ~< 50 um):



Different stages in the gas amplification process next to the anode wire.







#### **Ionization Cross Section: Townsend Coefficient**

Multiplication of ionization is described by the first Townsend coefficient  $-\alpha(E)$ 


$$dn = n\alpha dx$$
  $\alpha = \frac{1}{\lambda}$   $\lambda$  – mean free path


$$n = n_0 e^{\alpha(E)x}$$
 or  $n = n_0 e^{\alpha(r)x}$ 

- $\checkmark$   $\alpha(E)$  is determined by the excitation and ionization cross sections of the electrons in the gas.
- ✓ It depends also on various and complex energy transfer mechanisms between gas molecules.
- ✓ There is no fundamental expression for α(E) → it has to be measured for every mixture.

$$M = \frac{n}{n_0} = \exp\left[\int_a^{r_C} \alpha(r)dr\right]$$


Amplification factor or Gain





## **Ionization Cross Section: Penning Effects**

- ✓ Additional ionizing energy transfer mechanisms due to the excited noble gas atoms, called collisional Penning energy transfers, occur when the excitation energy of a noble gas is higher than the ionization potential of an admixture gas.
- ✓ The energy transfer rate, probability that an excited atom ionizes a quenching agent, is a priori not known for a mixture but can be extracted from the fits of the experimental gas gain data using the Magboltz simulations
- ✓ For example, the impact of the Penning effect on gas gain is roughly a factor 10 in Ar-CO2 mixtures and exceeding a factor of 100 in Ar-C2H2 mixtures




The Penning transfer rate  $r_p$  is measured by finding the fraction of the excitations to be added to  $\alpha$  so that the measured gain is reproduced:

$$G = \exp \int \alpha \left[ 1 + r_{p} \frac{V_{exc}}{V_{ion}} \right]$$

 $ightharpoonup r_{p}$  depends on gas choice, quencher fraction and density.

Ar/CO2 transfer rates:




- ✓ Collisional energy transfer mostly scales linearly with the gas pressure and the fraction of quenching gas in the mixture, while ionization by photons emitted from excitations is independent of the medium.
- ✓ In addition, collisional Penning transfers of some higher excited states can occur before they decay at atmopheric pressure and are not restricted to metastable states of the excited noble gas.

## Operation Modes of Gas Detector: Gain-Voltage Characteristics

#### √ Ionization mode (II):

- → full charge collection, but no multiplication gain = 1
- ✓ Proportional mode (IIIA):
  - → Multiplication of ionization starts; detected signal proportional to original ionization → possible energy measurement (dE/dx)
  - → proportional region (gain ~ 10³ 10⁴)
  - → semi-proportional region (gain ~ 10⁴ 10⁵), space charge effects
  - → secondary avalanches need quenching
- ✓ Limited proportional mode (saturated, streamer) (IIIB):
  - → saturation (gain > 10<sup>6</sup>), independent of number of primary electrons
  - → streamer (gain > 10<sup>7</sup>), avalanche along the particle track
- ✓ Geiger mode (IV):
  - → Limited Geiger region: avalanche propogated by UV photons;
  - → Geiger region (gain > 10°), avalanche along the entire wire



## Wire Proportional Counter: Signal Development

Incremental charge induced by Q moving through dV:

$$dQ = \frac{Q}{V_0}dV = \frac{Q}{V_0}\frac{dV}{dr}dr$$

Assuming that the total charge of the avalanche Q is produced at a (small) distance I from the anode, the electron and ion contributions to the induced charge are:

$$q^{-} = \frac{Q}{V_0} \int_{a}^{a + \lambda} \frac{dV}{dr} dr = -\frac{QC}{2\pi\varepsilon_0} \ln \frac{a + \lambda}{a}$$
 and 
$$q^{+} = \frac{Q}{V_0} \int_{a + \lambda}^{b} \frac{dV}{dr} dr = -\frac{QC}{2\pi\varepsilon_0} \ln \frac{b}{a + \lambda}$$

$$q^{+} = \frac{Q}{V_0} \int_{a+\lambda}^{b} \frac{dV}{dr} dr = -\frac{QC}{2\pi\varepsilon_0} \ln \frac{b}{a+\lambda}$$

The total induced signal is 
$$q = q^- + q^+ = -\frac{QC}{2\pi\varepsilon_0} \ln\frac{b}{a} = -Q$$
 on the anode (+Q on the cathode)

The ratio of electron and ion contributions: 
$$\frac{q^{-}}{q^{+}} = \frac{\ln(a+\lambda) - \ln a}{\ln b - \ln(a+\lambda)}$$

The electron-induced signal is negligible For a counter with  $a=10\mu m$ , b=10 m:  $q^{-1}/q^{+} \sim 1\%$ 


Neglecting electrons, and assuming all ions leave from the wire surface:

$$q(t) = q^{+}(t) = -\int_{0}^{t} dq = -\frac{QC}{2\pi\varepsilon_{0}} \ln \frac{r(t)}{a}$$
  $\frac{dr}{dt} = \mu^{+}E = \frac{\mu^{+}CV_{0}}{2\pi\varepsilon_{0}} \frac{1}{r}$ 

$$q(t) = -\frac{QC}{2\pi\varepsilon_0} \ln\left(1 + \frac{\mu^+ CV_0}{2\pi\varepsilon_0 a^2}t\right) = -\frac{QC}{2\pi\varepsilon_0} \ln\left(1 + \frac{t}{t_0}\right) i(t) = -\frac{QC}{2\pi\varepsilon_0} \frac{1}{t_0 + t}$$

Total ions drift time:

$$T^{+} = \frac{\pi \varepsilon_0 (b^2 - a^2)}{\mu^{+} C V_0}$$
  $q(T^{+}) = -Q$ 



## **Useful Write-Ups on Gaseous Detectors**

Wire & Drift Chamber Basics

CERN 77-09 3 May 1977

ORGANISATION EUROPÉENNE POUR LA RECHERCHE NUCLÉAIRE CERN EUROPEAN ORGANIZATION FOR NUCLEAR RESEARCH

PRINCIPLES OF OPERATION OF MULTIWIRE
PROPORTIONAL AND DRIFT CHAMBERS


F. Sauli

Lectures given in the
Academic Training Programme of CERN
1975-1976

GENEVA


1977

More on signal theorems, readout electronics etc. can be found in:




## **Multi-Wire Proportional Chamber (MWPC)**

Simple idea to multiply SWPC cell -> First electronic device allowing high statistics experiments !!



High-rate MWPC with digital readout: Spatial resolution is limited to  $s_x \sim s/sqrt(12) \sim 300 \mu m$ 

TWO-DIMENSIONAL MWPC READOUT CATHODE INDUCED CHARGE (Charpak and Sauli, 1973)



Spatial resolution determined by: Signal / Noise Ratio
Typical (i.e. 'very good') values: S ~ 20000 e: noise ~ 1000e

Space resolution < 100 μm

## Multi-Wire Proportional Chamber (MWPC): Wire Displacements


Resolution of MWPCs limited by wire spacing better resolution  $\rightarrow$  shorter wire spacing  $\rightarrow$  more (and more) wires...

#### ✓ Small wire displacements reduce field quality

**Table 35.1:** Maximum tension  $T_M$  and stable unsupported length  $L_M$  for tungsten wires with spacing s, operated at  $V_0 = 5$  kV. No safety factor is included.

Wire diameter ( $\mu$ m)	$T_M$ (newton)	s (mm)	$L_M$ (cm)
10	0.16	1	25
20	0.65	2	85

- ✓ Need high mechanical precision both for geometry and wire tension ... (electrostatic and gravitation, wire sag ...)
- Several simplifying assumptions are made in analytical calculations: electrostatic force acting on the wire does not change during wire movements, or varies linearly with the displacement, the wire shape is parabolic; only one wire moves at a time.
- The advantage of numerical integrations using Garfield++ program is to simulate the collective movement of all wires, which are difficult analytically, and to consider all forces acting on a wire: forces between anode wire and other electrodes (wires, cathode) & gravitational force



## **MWPC: First Presentation and First Large Experiment**

colloque international sur l'électronique nucléaire First presentation:

international VERSAILLES, symposium 10-13 September 1968 on nuclear electronics

## Chambres à Etincelles

Spark chambers

Rapporteur Reporter M. CHARPAK CERN - GENEVE (Suisse)

Secrétaire scientifique Scientific

Secretary

M. FEUVRAIS
Faculté des Sciences - Lyon
(France)



#### First Large Experiiment:

1972-1983: SPLIT FIELD MAGNET DETECTOR: ~ 40 LARGE AREA MWPCs @ CERN ISR



## 1968: Multi – Wire Proportional Chamber (MWPC)

NUCLEAR INSTRUMENTS AND METHODS 62 (1968) 262-268; © NORTH-HOLLAND PUBLISHING CO.

#### THE USE OF MULTIWIRE PROPORTIONAL COUNTERS TO SELECT AND LOCALIZE CHARGED PARTICLES

G. CHARPAK, R. BOUCLIER, T. BRESSANI, J. FAVIER and Č. ZUPANČIČ

CERN, Geneva, Switzerland

Received 27 February 1968

Properties of chambers made of planes of independent wires placed between two plane electrodes have been investigated. A direct voltage is applied to the wires. It has been checked that each wire works as an independent proportional counter down to separations of 0.1 cm between wires.

Counting rates of 105/wire are easily reached; time resolutions

of the order of 100 nsee have been obtained in some gases; it is possible to measure the position of the tracks between the wires using the time delay of the pulses; energy resolution comparable to the one obtained with the best cylindrical chambers is observed; the chambers operate in strong magnetic fields.

Proportional counters with electrodes consisting of many parallel wires connected in parallel used for some years, for special application

plane of independent wires placed between two plane electrodes. Our observations show that such chambers offer properties that can make them more advantageous than wire chambers or scintillation hodoscopes for many applications.

#### 2. Construction

1. Introduction

Wires of stainless steel,  $4 \times 10^{-3}$  cm in diameter, are stretched between two planes of stainless-steel mesh, made from wires of  $5 \times 10^{-3}$  cm diameter,  $5 \times 10^{-2}$  cm apart. The distance between the mesh and the wires in 0.75 cm. We studied the properties of chambers with wire separation a = 0.1, 0.2, 0.3 and 1.0 cm. A strip of metal placed at 0.1 cm from the wires, at the same potential (fig. 1), plays the same role as the guard rings




Fig. 1. Some details of the construction of the multiwire chambers.

A copper shield protects the wires at their output from the chamber and contains the solid state amplifiers.

in cylindrical proportional chambers. It protects the wires against breakdown along the dielectrics. It is

#### G. Charpak et al., NIMA62 (1968) 262






Fig. 2. Equipotentials in a chamber. Wires of  $4 \times 10^{-6}$  cm diameter, 0.3 cm separation, and 1.5 cm total thickness. 20 V applied between the wires and the external mesh. Results from an analogic method.

#### ENERGY RESOLUTION ON 5.9 KeV:



## **DEPENDENCE OF COLLECTION TIME FROM TRACK'S DISTANCE:**






#### **Drift Chambers**

FIRST DRIFT CHAMBER OPERATION (H. WALENTA ~ 1971);
HIGH ACCURACY DRIFT CHAMBERS (Charpak-Breskin-Sauli ~ 1973-75)

THE ELECTRONS DRIFT TIME PROVIDES THE DISTANCE OF THE TRACK FROM THE ANODE:



Choose drift gases with little dependence  $v_D(E) \rightarrow$  linear space - time relation r(t)

Measure drift time  $t_D$  [need to know  $t_0$ ; fast scintillator, beam timing]

Determine location of original ionization:


$$x = x_0 \pm v_D \cdot t_D$$
$$y = y_0 \pm v_D \cdot t_D$$

If drift velocity changes along path:


$$x = \int_0^{t_D} v_D \, dt$$

In any case:

Need well-defined drift field ...



#### The spatial resolution is not limited to the cell size :



 $\sigma_x^2 = \left(\frac{1}{64N^2}\right) \cdot \frac{1}{x^2} + \underbrace{\frac{2D}{v_d} \cdot x}_{\text{diffusion}} + \underbrace{\sigma_{\text{const}}^2}_{\text{electronics}}$ 

Typical single point resolutions of drift chambers: 50...150 µm depends on length of the drift path

- ✓ primary ionization statistics: how many ion pairs, ionization fluctuations dominates close to the wire
- ✓ diffusion of electrons in gas: dominates for large drift length
- ✓ electronics: noise, shaping characteristics constant contribution (drift length independent)

## Wire & Drift Chambers: Wide-Spread Tool in HEP for > 40 Years



#### The Evolution of Drift Chambers and Future e+e- Colliders

		ρa	
CDEAD	MARK2	Drift Chamber	
SPEAR	MARK3	Drift Chamber	
DORIS	PLUTO	MWPC	
DORIS	ARGUS	Drift Chamber	
CESR	CLEO1,2,3	Drift Chamber	
	CMD-2	Drift Chamber	
VEPP2/4M	KEDR	Drift Chamber	
	NSD	Drift Chamber	
Bittin.	CELLO	MWPC + Drift Ch.	
	JADE	Drift Chamber	
PETRA	PLUTO	MWPC	
idine:	MARK-J	TEC + Drift Ch.	
	TASSO	MWPC + Drift Ch.	
	AMY	Drift Chamber	
TRISTAN	VENUS	Drift Chamber	
	TOPAZ	TPC	

THE REAL PROPERTY.	MARK2	Drift Chamber
	PEP-4	TPC
PEP	MAC	Drift Chamber
	HRS	Drift Chamber
	DELCO	MWPC
BEPC	BES1,2	Drift Chamber
	ALEPH	TPC
LEP	DELPHI	TPC
LEF	L3	Si + TEC
	OPAL	Drift Chamber
SLC	MARK2	Drift Chamber
SLC	SLD	Drift Chamber
DAPHNE	KLOE	Drift Chamber
PEP2	BaBar	Drift Chamber
KEKB	Belle	Drift Chamber

		picse		
	VEPP2000	CMD-3	Drift Chamber	
VEPP4		KEDR	Drift Chamber	
	BEPC2	BES3	Drift Chamber	
	S.KEKB	Belle2	Drift Chamber	
	. 12 . 25	HARRIE		
		futui	е	
	ILC	ILD	TPC	
	ILC	SiD	Si	
	CLIC	CLIC	Si	
	500	CLD	<del>Ci</del>	
	FCC-ee	IDEA	Drift Chamber	
	o E Do	Baseline	TPC	
	CEPC	IDEA	Drift Chamber	
1111	SCTF	BINP	Drift Chamber	

nresent

#### Lesson #1 - from "open" to "closed" cell

- Lesson #3 small cells and He gas closec
- the tra He radiation length 50× longer than Ar
- square
   slower drift velocity implies smaller Lorenz angle for a given B-field
  - small He has a smaller cross section for low energy photons than Ar
    - small size cells limit the electron diffusion contribution to spatial resolution
- small size cells provide high granularity (improving occupancy) and allow for a larger number of hits per track, improving spatial resolution portior
- envelc ... but
- small
- portions of active volume not sampled between the cylindrical envelope of axial wires and the hyperboloid envelope of stereo wires accumulation of trapped electrons and ions in a region of very low field

closed

... but

#### longitudinal gain variation at boundaries between axial and stereo layers

#### spatial resolution dominated by ionization statistics for short drift distances adding more quencher to compensate, mitigates the advantage of He

#### Lesson #4 – full stereo configuration

STCF

- no gar electro
- consta
- larger.
- maxim two ste
- ... but
- open t from th
- consta
- z (radi consta

Lesson #5 – summary

**Drift Chamber** 

the configuration offering the best performance in terms of

**HIEPA** 

- momentum resolution is one with small, single sense wire closed cells, arranged in contiguous layers of opposite sign stereo angles,
- obtained with constant stereo angle transverse projection
- the gas mixture is based on helium with a small amount of guencher (90% He / 10% iC<sub>4</sub>H<sub>10</sub>, KLOE gas) which, besides low multiple
- scattering contribution, allows for the exploitation of the cluster timing technique, for improved spatial resolution, and of the cluster
- counting technique, for excellent particle identification
- suggested wire material is Ag coated Al, but lighter materials are under scrutiny (like metal coated carbon monofilaments)

An ultra-light drift chamber (IDEA concept) targetted for FCC-ee and CePC (100 km) was inspired by DAFNE KLOE Wire Chamber and by more recent version of it for MEG2 experiment

### Original Gaseous Detectors (mostly wires/straws RPC) in LHC Experiments

ALICE: TPC (tracker), TRD (transition rad.),
TOF (MRPC), HMPID (RICH-pad chamber),
Muon tracking (pad chamber), Muon
trigger (RPC)

ATLAS: TRD (straw tubes), MDT (muon drift tubes), Muon trigger (RPC, thin gap chambers)

CMS: Muon detector (drift tubes, CSC), RPC (muon trigger)

LHCb: Tracker (straw tubes), Muon detector (MWPC, GEM)

## **Original Gaseous Detectors in LHC Experiments**


	Vertex	Inner Tracker	PID/ photo- detecto r	EM CALO	HAD CALO	MUON Track	MUON Trigger
ATLAS	-	TRD (straws)	-	-	-	MDT (drift tubes), CSC	RPC, TGC (thin gap chambers)
CMS  TOTEM	-	-  GEM	-	-	-	Drift tubes, CSC	RPC, CSC
LHCb	-	Straw Tubes	-	-	-	MWPC	MWPC, GEM
ALICE	-	TPC (MWPC)	TOF (MRPC), HPMID (RICH- pad chamber), TRD (MWPC)	-	-	Muon pad chambers	RPC







## **ALICE Time Projection Chamber (TPC)**



- Largest TPC:
  - Length 5m
  - Diameter 5m
  - Volume 88m<sup>3</sup>
  - Detector area 32m<sup>2</sup>
  - Channels ~570 000
- High Voltage:
  - Cathode -100kV
- Material X₀
  - Cylinder from composite materials from airplane industry (X<sub>0</sub>= ~3%)

Precision in z: 250µm



End plates 250µm





Wire chamber: 40µm

- Track point recorded in 3-D
  - (2-D channels in x-y) x (1-D channel in  $z = v_{drift} x t_{drift}$ )
- Particle identification by dE/dx


long ionization track, segmented in 100-200 measurements

_			
	STAR	ALICE	ILC
Inner radius (cm)	50	85	32
Outer radius (cm)	200	250	170
Length (cm)	2 * 210	2 * 250	2 * 250
Charge collection	wire	wire	MPGD
Pad size (mm)	2.8 * 11.5	4 * 7.5	2 * 6
	6.2 * 19.5	6*10(15)	
Total # pads	140000	560000	1200000
Magnetic field [ T ]	0.5	0.5	4
Gas Mixture	Ar/CH4	Ne/CO2	Ar/CH4/CO2
	(90:10)	(90:10)	(93:5:2)
Drift Field [V/cm]	135	400	230
Total drift time (μs)	38	88	50
Diffusion σ <sub>T</sub> (μm/√cm)	230	220	70
Diffusion σ <sub>L</sub> (μm/√cm)	360	220	300
Resolution in rφ(μm)	500-2000	300-2000	70-150
Resolution in rz (μm)	1000-3000	600-2000	500-800
dE/dx resolution [%]	7	7	< 5
Tracking efficiency[%]	80	95	98

## **Gaseous Tracking @ LHC Experiments**

- ✓ Straw tubes (single-wire proportional counters) with xenon-based gas mixture
- ✓ 4 mm in diameter, equipped with a 30 µm diameter gold-plated W-Re wire

## **ATLAS TRT**




- Stable operation at very high rates up to 12 MHz/cm²
- ✓ Achieved spatial (time) resolution: 135 um (7 ns) at high intensity 2\* 108 s<sup>-1</sup>

# Open







CMS/TOTEM

## Muon Detectors: CMS Cathode Strip Chambers (CSC)

Muon detectors are tracking detectors (e.g. wire-based tubes):

- → they form the outer shell of the (LHC) detectors
- → they are not only sensitive to muons (but to all charged particles)!
- → just by "definition": if a particle has reached the muon detector (it's considered to be a muon); all other particles should have been absorbed in the calorimeters


#### Challenge for muon detectors:


- large surface to cover (outer shell); keep mechanical positioning stable over time
- also good knowledge of (inhomogeneous) magnetic field


CMS CSC: precise measurement of the second coordinate by interpolation of the signal induced on pads.

Closely spaced wires makes CSC fast detector.

CMS CSC









## **Muon Systems: Resistive Plate Chambers (RPC)**

– two resistive plates (~10 $^9$   $\Omega$  cm) with a small gas gap (2 mm) and large high voltage (12 kV) on outside electrodes

- strong E-field: operation in "streamer mode"
  - → gas avalanche starting in gas gap (no wires involved)
  - → developing of avalanche or "streamers" (blob with lots of charge)
  - → signal on external read-out strips via influence (segmented for position resolution)
  - → streamer/discharge is "self-quenching": stops when near-by resistive electrodes are locally discharged (E-field breaks down)

Experiment	Electrodes material & resistivity	Gas mixture	Operation mode; charge/track	Particle rates ; Accumulated charge
L3	Oiled bakelite 2*10 <sup>11</sup> Ω cm	Ar/iC <sub>4</sub> H <sub>10</sub> /C <sub>2</sub> H <sub>2</sub> F <sub>4</sub> (57:37:6)	Streamer	Consistent with cosmic rays
Belle	Float glass 10 <sup>12</sup> -10 <sup>13</sup> Ωcm	Ar/iC <sub>4</sub> H <sub>10</sub> /C <sub>2</sub> H <sub>2</sub> F <sub>4</sub> (30:8:62)	Streamer	~10-20 Hz/cm <sup>2</sup> ;
BaBar	Oiled bakelite	Ar/iC <sub>4</sub> H <sub>10</sub> /C <sub>2</sub> H <sub>2</sub> F <sub>4</sub>	Streamer	~10-20 Hz/cm <sup>2</sup> ;
	10 <sup>11</sup> - 10 <sup>12</sup> Ωcm	(60.6:4.7:34.7)	1000pC/track	<10 C/cm <sup>2</sup> (in 2010)
ATLAS	Oiled bakelite	C <sub>2</sub> H <sub>2</sub> F <sub>4</sub> /'iC <sub>4</sub> H <sub>10</sub> /	Avalanche	<0.1 kHz/cm <sup>2</sup> ;
	2*10 <sup>10</sup> Ωcm	SF <sub>6</sub> (96.7:3:0.3)	30 pC/track	<0.3 C/cm <sup>2</sup>
CMS	Oiled bakelite:	C <sub>2</sub> H <sub>2</sub> F <sub>4</sub> /'iC <sub>4</sub> H <sub>10</sub> /	Avalanche	<0.1 kHz/cm <sup>2</sup> ;
barrel	10 <sup>10</sup> Ωcm	SF <sub>6</sub> (96:3.5:0.5)	30 pC/track	<0.3 C/cm <sup>2</sup>
ALICE	Oiled bakelite 3*10 <sup>9</sup> Ωcm	Ar/iC <sub>4</sub> H <sub>10</sub> /C <sub>2</sub> H <sub>2</sub> F <sub>4</sub> / SF <sub>6</sub> (49:40:7:1)	Streamer	<0.1 kHz/cm <sup>2</sup> ; <0.2 C/cm <sup>2</sup>
LHC-b	Oiled bakelite	C <sub>2</sub> H <sub>2</sub> F <sub>4</sub> /'iC <sub>4</sub> H <sub>10</sub> /	Avalanche	0.25-0.75kHz/cm <sup>2</sup>
	9*10 <sup>9</sup> Ωcm	SF <sub>6</sub> (95:4:1)	30 pC/track	0.35-1.1 C/cm <sup>2</sup>





#### Advantages:

- > simple device, good to cover large areas,
- used as trigger devices in LHC experiments, BX trigger (25 ns)

#### Disadvantages:

→ Choice of resistive material + surface quality crucial, affects "dark" trigger rate


## **ALICE Multi-Gap RPC: Timing Resolution**


Relevant scale in HEP: t ~ L(m)/c ~ o(ns)


$$T_1 - T_2 = \frac{L}{c} \left( \frac{1}{\beta_1} - \frac{1}{\beta_2} \right) = \frac{L}{c} \left( \sqrt{1 + m_1^2/p^2} - \sqrt{1 + m_2^2/p^2} \right) \cong (m_1^2 - m_2^2) L / 2cp^2$$

- Traditional technique:
  - Scintillator + PMT ~ o (100 psec)
- Breakthrough with a spark discharge in gas
  - Pestov counter → ALICE MRPC ~ 60psec

ALICE-TOF has 10 gaps (two stacks of 5 gas gaps); each gap is 250 micron wide







Technology	Time resolution
Pestov Counter	30-50 ps
• RPC	~ 1-5 ns (MIP)
MultiGap RPC	~ 50 ps (MIP)
• GEM	~ 1-2 ns (UV) ~ 5-10 ns (MIP)
Micromegas	~ 700 ps (UV) ~ 5-10 ps (MIP)


## **ALICE MDT: Resolution Limits of High-Rate Wire Chambers**


#### L3 Muon Spectrometer (LEP):

~ 40000 chan. ;  $\sigma$  (chamber) < 200  $\mu$ m


#### ATLAS Muon Drift Tubes (LHC):

- ~ 1200 chambers,  $\sigma$  (chamber) ~ 50  $\mu$ m
  - 370000 tubes, 740000 end-plugs
  - 12000 CCD for optical alignment






Intrinsic limitation of wire chambers: (resolution degradation at high rates):





1 chamber → 2 layers of 3 drift tubes

Spatial resolution /chamber (2 layers of 3 drift tubes)




# Micro-Pattern Gaseous Detectors: Bridging the Gap for Tracking between Wire Chambers and Silicon-based Devices









#### Advantages of gas detectors:

- low radiation length
- large areas at low price
- flexible geometry
- spatial, energy resolution ...

#### **Problem:**


✓ rate capability limited by space charge defined by the time of evacuation of positive ions

#### **Solution:**

✓ reduction of the size of the detecting cell (limitation of the length of the ion path) using chemical etching and photo-lithographique techniques developed for microelectronics and keeping at same time similar field shape.


## Micro-Strip Gas Chamber (MSGC): An Early MPGD

Multi-Wire Proportional Chamber (MWPC)




Micro-Strip Gas Chamber (MSGC)

Typical distance between wires limited to ~1 mm due to mechanical and electrostatic forces




Excellent spatial resolution

MSGC significantly improves rate capability due to fast removal of positive ions




Typical distance between electrodes ~100 μm



## Micro-Strip Gas Chamber (MSGC): Discharge Problems

For efficient detection of minimum ionizing tracks a gain ~ 5000 is needed:

- → No discharges with X-rays and electrons;
- → Discharge probability is large ~ many per min (heavy ionizing particles)






Induced discharges are intrinsic property of all single stage MPGDs in hadronic beams (MSGC turned out to be prone to irreversible damages)

## Micro-Strip Gas Chamber (MSGC): Discharge Problems


Major processes leading at high rates to MSGC operating instabilities:

- ✓ Substrate charging-up and time-dependent modification of the E field
  - → slightly conductive support




- ✓ Deposition of polymers (aging)
   → validation of gases, material
  - → validation of gases, materials, gas systems
- Discharges under exposure to highly ionizing particles
  - → multistage amplification, resistive anodes


FIELD EMISSION FROM CATHODE EDGE



CHARGE PRE-AMPLIFICATION FOR IONIZATION RELEASED IN HIGH FIELD CLOSE TO CATHODE



VERY HIGH IONIZATION RELEASE FROM HEAVILY IONIZING PARTICLES




High Fields

**Small Gap** 

Discharge


Valid for all micro-pattern detectors
- Law of Nature!!!

## **MSGC Discharge Problems**




**FULL BREAKDOWN** 

## **MSGC In Experiments**



**Telescope of 32 MSGCs** tested at PSI inNov99 (CMS Milestone)




# MSGC-GEM detectors R<sub>min</sub> ~ 6 cm

HERA-B Inner Tracker

⇒ 10<sup>6</sup> particles/cm<sup>2</sup> s 300 um pitch

184 chambers: max 25x25 cm<sup>2</sup>

~ 10 m²; 140.000 channels



## The D20 diffractometer MSGC is working since Sept 2000

1D localisation 48 MSGC plates (8 cm x 15 cm)

Substrate: Schott S8900

Angular coverage : 160° x 5,8°

Position resolution : 2.57 mm ( 0,1°)

5 cm gap; 1.2 bar CF4 + 2.8 bars 3He

#### **DIRAC**

4 planes MSGC-GEM Planes 10x10 cm<sup>2</sup>

## **Aging Phenomena in Wire Chambers**

plack magic. Avalanche formation close to wire can be considered as a micro plasma discharge ...and plasma chemistry not well understood in general:

Whereas most ionization processes require electron energies > 10 eV, the breaking of chemical bonds and formation of free radicals requires ~ 3-4 eV

- dissociation of detector gas and pollutants
- formation of highly active radicals (many expected to have large dipole moments)
- polymerization of organic quenchers
- insulating deposits on anodes and cathodes



Anode: increase of wire diameter reduced and variable E-field variable gain and energy resolution



Cathode: ions on top of insulating layer (Malter cannot recombine built-up of **Effect)** strong E-field across insulating electron field emission and microdischarges

NUCLEAR INSTRUMENTS AND METHODS 99 (1972) 279-284; © NORTH-HOLLAND PUBLISHING CO.

#### TIME DEGENERACY OF MULTIWIRE PROPORTIONAL CHAMBERS

G. CHARPAK, H. G. FISHER, C. R. GRUHN, A. MINTEN, F. SAULI and G. PLCH

CERN, Geneva, Switzerland

and


G. FLÜGGE


1972:

II. Institut für Experimentalphysik, Hamburg, Germany

Received 28 May 1971

The deterioration with time of multiwire proportional chambers lifetime can be obtained without changing the properties of the using isobutane as one component of the gas mixture is studied. gas mixture. Irradiation tests of 5 × 1010/cm2 have not shown any It is shown that by addition of methylal among others, a long alteration in the chamber performance





## Aging Phenomena in Wire Chambers: 1st Workshop (1986)


First systematic attempts to summarize aging results and to provide remedies minimizing wire chamber aging

Proceedings of the Workshop on Radiation Damage to Wire Chambers

1986:

Lawrence Berkeley Laboratory, Berkeley, California

January 16-17, 1986



April 1986

Lawrence Berkeley Laboratory University of California Berkeley, California 947'20 Nuclear Instruments and Methods in Physics Research A252 (1986) 547-563 North-Holland, Amsterdam

REVIEW OF WIRE CHAMBER AGING \*

J. VA'VRA

Stanford Linear Accelerator Center, Stanford University, Stanford, California 04305, USA

This paper makes an overview of the wire chamber aging problems as a function of various chamber design parameters. It emphasizes the chemistry point of view and many examples are drawn from the plasma chemistry field as a guidance for a possible effort in the wire chamber field. The paper emphasizes the necessity of tuning of variables, the importance of purity of the wire chamber environment as well as it provides a practical list of presently known recommendations. In addition, several models of the wire chamber aging are qualitatively discussed. The paper is based on a summary talk given at the Wire Chamber Aging Workshop held at LBL, Berkeley on January 16-17, 1986. Presented also at Wire Chamber Conference, Vienna, February 25-28, 1986.

436

Nuclear Instruments and Methods in Physics Research A300 (1991) 436–479

North-Holland

Wire chamber aging \*

John A. Kadyk

Lawrence Berkeley Laboratory, 1 Cyclotron Road, Berkeley, CA 94720, USA

Received 27 June 1990

An overview of wire chamber aging is presented. A history of wire aging studies and the manifestations of wire aging are reviewed. Fundamental chemical principles relating to wire chamber operation are presented, and the dependences of wire aging on certain wire chamber operating parameters are discussed. Aging results from experimental detectors and laboratory experiments are summarized. Techniques for analysis of wire deposits and compositions of such deposits are discussed. Some effects of wire material and gas additives on wire aging are interpreted in chemical terms. A chemical model of wire aging is developed, and similarities of wire chamber plasmas to low-pressure rf-discharge plasmas are suggested. Procedures recommended for reducing wire aging effects are summarized.

Harmful are: halogen or halocarbons, silicon compounds, oil, fats ... CO<sub>2</sub> helps with water, and alcohol admixtures

547

## Aging Phenomena in Gaseous Detectors: 2<sup>nd</sup> Workshop (2001)

IEEE TRANSACTIONS ON NUCLEAR SCIENCE, VOL. 49, NO. 4, AUGUST 2002

Summary and Outlook of the International Workshop on Aging Phenomena in Gaseous Detectors (DESY, Hamburg, October 2001)

M. Titov, M. Hohlmann, C. Padilla, and N. Tesch

arXiv:physics/0403055 v1 9 March 2004

RADIATION DAMAGE AND LONG-TERM AGING IN GAS DETECTORS<sup>1</sup>

#### MAXIM TITOV

Institute of Physics, Albert-Ludwigs University of Freiburg, Hermann-Herder Str. 3, Freiburg, D79104, Germany and

Institute of Theoretical and Experimental Physics (ITEP), B. Cheremushkinskaya, 25, Moscow, 117259, Russia

- ✓ The HERA-B Experiment was the first high-rate experiment, which addressed SYSTEMATICALLY aging phenomena in gas detectors, followed later by ALL LHC experiments
- ✓ Many ORIGINAL PROBLEMS in HIGH RATE GAS DETECTORS were due to CASUAL SELECTION of chamber designs, gas mixtures, materials and gas system components, which worked at "low rates", but failed in high-rate environments




	Table 1. Aging results with wire detector prototypes for the use at high energy physics facilities.						
Experiment,	Gas Mixture	Gain	Cathode	Charge	Gas gain (G); Current		
Detector,		reduction/	aging	C/cm	density(I); Rate (R); Irradiated		
Reference		etching			area (S)		
HERA-B	Ar/CF <sub>4</sub> /CO <sub>2</sub>	No/Au	No	0.6	G~3*104; I~0.4-0.9µA/cm;		
OTR [34]	(65:30:5)	damage			100MeV n. beam; S-50cm²		
HERA-B	Ar/CF <sub>4</sub> /CO <sub>2</sub>	No	No/F-film	0.7	G~10 <sup>4</sup> -10 <sup>5</sup> ; I ~ 0.3μA/cm;		
MU ON [35]	(65:30:5)		on Al cath.		R<10 <sup>5</sup> Hz/cm <sup>2</sup> ; S~1200cm <sup>2</sup>		
HERA-B	Ar/CF <sub>4</sub>	No	Ne	0.07	G~10°; I ~ 0.15µA/cm;		
MUON[35]	(70:30)				R~10° Hz/cm²; S~150cm²		
ATLAS	Xe/CF <sub>4</sub> /CO <sub>2</sub>	No	No	20	G~ 3*10 <sup>4</sup> ; I ~ 0.7 μA/cm;		
TRT [15,48]	(70:20:10)				S-24 cm2		
Straw	Xe/CF <sub>4</sub> /CO <sub>2</sub>	No/Au	No	9	G~3*10 <sup>4</sup> : I ~ 1.7µA/cm:		
R&D[45]	(70:20:				m²		
Straw	Ar/CF4/	A /!					
R&D[45]	(60:10:	vvir	e cr	ıan	nbers 💹		
CMS	Ar/CF4/	• • • • •	<b>-</b>				
MU ON [14]	(40:10:50)	cracks	on Cucain.	ı	R~Z*1U HZ/cm*; S~1cm²		
CMS	Ar/CFa/CO2	No	Si-F film	0.4	G~10°; I < 0.05 µA/cm;		
MU ON [46]	(40:10:50)		on Cu cath.		R-2*104 Hz/cm2:S-21000cm2		
LHC-B	Ar/CF <sub>4</sub> /CO <sub>2</sub>	No	Etching of	0.25	G-10°; I < 0.03 µA/cm;		
MU ON [52]	(40:10:50)		FR4 bars		R-3*104Hz/cm2; S-1500cm2		
COMPASS	Ar/CF <sub>4</sub> /CO <sub>2</sub>	Ne/Si-	Ne	1.1	G~4*10 <sup>4</sup> ; I ~ 4 μA/cm;		
Straws [53]	(74:20:6)	traces			R-2*108 Hz/cm2; S-3 cm2		
HERMES	Ar/CF <sub>4</sub> /CO <sub>2</sub>	No	Al etching/	9	G~5*10 <sup>5</sup> ; I ~ 1 μA/cm;		
FD [47]	(90:5:5)		Cldeposits		R~105 Hz/cm2; S~7 cm2		
ATLAS	Xe/CO <sub>2</sub> /O <sub>2</sub>	No	No	11	G~ 3*10 <sup>4</sup> ; I ~ 1-3 µA/cm;		
TRT[16]	(70:27:3)				S-1 cm²		
ATLAS	Xe/CO <sub>2</sub> /O <sub>2</sub>	No/Si-	No	0.3	G~3*10': I ~ 0.1 µA/cm:		
TRT[16]	(70:27:3)	deposits			S-1 cm²		
ATLAS	Ar/CO	No	No	0.7	I~ 0.1µA/cm;		
MDT[55]	(90:10)				R-4*10 <sup>2</sup> Hz/cm <sup>2</sup> ; S-7500cm <sup>2</sup>		
ATLAS	Ar/CO	No	No	>1.5	G~2*10 <sup>4</sup> ; I ~ 0.05-0.2µA/cm;		
MDT[56]	(93:7)				R-8*10 <sup>2</sup> -10 <sup>4</sup> Hz/cm <sup>2</sup> ; S-90cm <sup>2</sup>		
ATLAS	Ar/CO	Yes/Si-	No	0.2	G~9*10 <sup>4</sup> ; I ~ 0.02µA/cm;		
MDT[57]	(93:7)	deposits	"		R~5*10 <sup>2</sup> Hz/cm <sup>2</sup> :S~15000cm <sup>2</sup>		
CMS	Ar/CO	Yes/ Si	No	0.76	G~6*10'; I ~ 2 µA/cm;		
MUON[14]	(30:70)	deposits			R-2*10 <sup>6</sup> Hz/cm <sup>2</sup> : S~1 cm <sup>2</sup>		
stdrd	(110)	<u>r</u> <b>u</b>			ica io machi, b- rem		

Tabl	Table 2. Summary of aging experience with Micro-Pattern Gas Detectors.						
Detector type	Micture	Chin	Charge	Current.	Irradiate dare a:	Irrad.	
		reduction	m.C/mm²	density	Irradiationrate	source	
		A C¥C÷		density, nA/mm²			
MSGC	Ar/DME	No	200	10	3 mm <sup>1</sup> :	6.4 keV	
[65,104]	00:10		200		10° Hz/mm²	X-rays:	
MS GC 1661	AT/DME	No	40	63	03*0.8mm.	5.4 keV	
um oc feel	(50:50)		. ~	05	8*10° Hz/mm²	X-rays	
MSGC	Ar/DME	Anole	50	0	03*0.8mm.	5.4 keV	
[66]	(50:50)	deposit	_~	1 -	2*10" Hz/mm.	X-rays	
MS GC+ GEM	AT/DME	No	70	63	03*0.8mm <sup>1</sup>	5.4 keV	
[66]	(90:10)		"		2*10° Hz/mm²	X-rays	
MS GC+GEM	Ar/DME	No	- 5	2	~ 113 mm¹:	8keV	
1511	(50:50)		"	1 -	2*10" Hz/mm.1	X-rays	
MS GC+ GEM	Ar/DME	Yes	0.5	1	~ 900 mm <sup>1</sup> :	8keV	
151]	(50:50)	16	0.5		10 Hz/mm	X-rays	
MS GC+ GEM	(50.50)			2	350 mm <sup>1</sup>	8 keV	
1511				-	2*10* Hz/mm.1	X-rays	
Double GEM		-		- 6	2 mm <sup>1</sup> ;	5.4 keV	
		PGL	10		7*10 Hz/mm³		
[67]	- IVII	GL	<b>7</b> 3	13		X-rays	
Triple GEM				13	15 mm <sup>1</sup> ,	5.4 keV	
[68]	1 100				6*10" Hz/mm.1	X-rays	
Double GEM	Ar/CO <sub>1</sub>	No	12	4	200 mma <sup>1</sup> ;	6 keV	
[0]	(70:30)				5*10 Hz/mm²	X-rays	
Triple GEM	Ar/CO <sub>1</sub>	No	11	10	1260 mm <sup>1</sup> ;	8 9 keV	
[70]	(70:30)				2*10° Hz/mm¹	X-rays	
Triple GEM	Ar/CF./CO <sub>1</sub>	< 5 %	230	270	1 mm <sup>1</sup> ;	5.9 keV	
[71,72]	(60:20:20)				5*10° Hz/mm¹	X-rays	
Triple GEM	Ar/CFJ/CO <sub>1</sub>	< 5 %	45	160	1 mm¹;	5 9 keV	
[72]	(45:40:15)				5*10° Hz/mm¹	X-rays	
Triple GEM	Ar/CF./CO.	Yes/	20	20	200*240 mm²	25 kG	
[73]	(45:40:15)	55%				ωCo	
Triple GEM	Ar/CF/C,H <sub>ip</sub>	~ 10 %	110	160	1 mm¹;	5.9 keV	
[72]	(65:28:7)				5*10° Hz/mm¹	X-rays	
Triple GEM+	CT. (100)	No	0.1	3	100 mm <sup>1</sup> ;	Hg UV	
Cs1[88]	' '				10° Hzámm¹	Lamp	
Micromegas	Ne/ C.H p	Ye/	10	50	16 mm¹; 33Hz	53 MeV	
[74]	(91:9)	35 %	1	1	spankrate	m/s	
Micromegas	Ar/CF.	No	2	10		8keV	
[75]	(95:5)			1		X-rays	
Micromegas	CE/C.H.	No	1.6	25	20 mm²:	8 keV	
[76]	(94:6)			1	10°Hz/mm.1	X-rays	
Micromegas	Ar/C.H.	No	18	20	20 mm <sup>1</sup> ;	8 keV	
1761	046	1	"	1	2*10° Hz/mm²	X-rays	
Micronegas+	Ar/CO.	No	23	17	3 mm <sup>1</sup>	5.4 keV	
GEMI771	(70:30)		1 -	I - '		X-rays	
MS GC+ GEM	AT/DME	10% eff.	0.01	0.05	100*100 mm <sup>1</sup> :	24 GeV	
DIRAC [64]	(60:40)	drop	1	1.00	3*10 Hzámm	rarotans	
3- GEM [78]	Ar/CO.	No	2.3		310*310 mm <sup>1</sup> ;	Compass	
COMPASS	(70:30)	1 40	2.3	1 "	2*10°Hzámm¹	Beam	
CONTRACT	(10.30)			1	L IV MEANUIL	Dealit	

## **Aging Phenomena in Gaseous Detectors**

Implicit aging rate is proportional only to the total accumulated charge assumption:

$$R = -(1/G)(dG/dQ)$$
 (% per C/cm) (Kadyk'1985)

Aging phenomena depends on many highly correlated parameters:

#### Microscopic parameters:



#### Macroscopic parameters:

- √ Cross-sections
- ✓ Electron or photon energies
- ✓ Electron, ion, radical densities
- **✓** ...



There are simply too many variables in the problem ->

would be too naive to expect that one can express the aging rate using a single variable (C/cm)

- Gas mixture (nature of gas, trace contaminants)
- ✓ Gas flow & Pressure
- ✓ Geometry/material of electrodes & configuration of electric field
- ✓ Construction materials
- Radiation intensity
- ✓ Gas gain, ionization density
- ✓ Size of irradiation area

~1980


CLASSICAL AGING:

'NEW AGING' EFFECTS:

~2000

## **Aging Phenomena in Gaseous Detectors**

- ✓ Early aging studies of MSGCs indicated that they are much more susceptible to aging than wire chambers, potentially due to the filigree nature of MSGC structures and catalytic effects on the MSGC substrate
- ✓ More robust detectors (GEM, Micromegas) are better suited for the high-rate environments than MSGC and Wire-type detectors



# **Building Radiation-Hard Gas Detector (2001): Rules of Thumb**

- ✓ Build a "full-size prototype" (the smallest independent element of your detector)
- Expose full detector area of to the real radiation profile (particle type, gas gain, ionization density)
- Choose your gas mixtures (hydrocarbons are not trustable) and materials very carefully
- ✓ Vary all parameters systematically (gas gain, irradiation intensity, gas flow, ...) and verify your assumptions -> make aging studies on several identical prototypes
- Do not extrapolate aging results for any given parameter by more than an order of magnitude
- ✓ If you observed unexpected result understand the reason and reproduce results ...

Gaseous Detectors 6-10 Nov 2023 3<sup>rd</sup> Conference on Detector Stability and CERN Europe/Zurich timezone Aging Phenomena in Gaseous Detectors (Nover6+10, 2023, CERN) Local Organizing Committee and Gaseous detectors for particle physics are entering a phase where operation at current experiments and International Program future facilities will require the capacity to work at unprecedent particle rate, higher rate capability, Committee integrated charge and improved time resolution. In addition, new materials are in many cases needed to Official news and achieve these new requirements. Finally, the need to replace environmentally unfriendly gases has set bulletins an additional challenge to the community. The third International Conference on Detector Stability and Aging Phenomena in Gaseous Detectors aims in offering an occasion for sharing new results, new ideas, new facility requirements, roberto.guida@cern.ch

and in 2001 at DESY (Hamburg).

The conference will be held at CFRN in the main Auditorium from November 6<sup>th</sup> to 10<sup>th</sup>, 2023 The conference will continue the initiative started in 1986 with the first workshop held at LBL (Berkley)

International Conference on Detector Stability and Aging Phenomena in

Conference topics will include:

- · Detector stability and performance
- Aging phenomena
- Radiation hardness
- Material outgassing
- Novel materials
- Electrodes
- Photocathodes
- Plasma chemistry
- Environmentally friendly gases
- Gas and material analysis, characterisation, instruments
- Discharge damage and mitigation
- Front End Electronics for detector stability and aging mitigation

The conference will have invited reviews and selected contributions, as well as a poster session.

https://indico.cern.ch/event/1237829

The conference proceeding will be published in peer-reviewed journal.

## Micro-Pattern Gaseous Detector Technologies (MPGD)


Rate Capability: MWPC vs GEM:


- ✓ Micromegas
- ✓ Gas Electron Multiplier (GEM)
- ✓ Thick-GEM (LEM), Hole-Type & RETGEM
- ✓ MPDG with CMOS pixel ASICs ("GridPix")
- ✓ Micro-Pixel Chamber (µ–PIC)
- √ μ–Resistive WELL (μ-RWELL)
- ✓ Resistive-Plate WELL (RPWELL)


#### Micromegas


# 


#### GEM THGEM
























# **Gas Electron Multiplier (GEM)**

#### Thin metal-coated polymer foil chemically pierced by a high density of holes

A difference of potentials of ~ 500V is applied between the two GEM electrodes.

→ the primary electrons released by the ionizing particle, drift towards the holes where the high electric field triggers the electron multiplication process.




- ✓ A fast signal can be detected on the lower GEM electrode for triggering or energy discrimination.
- ✓ All readout electrodes are at ground potential.
- ✓ Positive ions partially collected on GEM electrodes

# **Avalanche Simulation in GEM & Triple-GEM Structures**


Animation of the avalanche process (Garfield++): monitor in ns-time electron/ion drifting and multiplication in GEM

Full decoupling of amplification stage (GEM) and readout stage (PCB, anode)




Amplification and readout structures can be optimized independently!

http://cern.ch/garfieldpp/examples/gemgain












# Micro Mesh Gaseous Structure (MICROMEGAS)

Micromesh Gaseous Chamber: micromesh supported by 50-100 mm insulating pillars


Small gap: fast collection of ions




# Other MPGDs Concepts: THGEM, µRWELL, RPWELL

THGEM Manufactured by standard PCB techniques of precise drilling in G10 (and other materials) and Cu etching

#### STANDARD GEM



#### **THGEM**




0.1 mm rim to prevent discharges

L. Periale, NIMA478 (2002) 377 LEM!: P. Jeanneret, PhD thesis, 2001


# µRWELL and RPWELL

#### High-rate µRWELL prototypes made by new techniques




https://indico.cem.ch/event/889380/contributions/4020066/attachments/ 2115302/3560600/RD51\_collabration\_meeting\_YouLwpptx

# µRWELL with 2D-Strip Readout — For RD51 Tracker



https://indico.cem.ch/event/1040996/contributions/4404219/attachments/ 2266859/3849374/2021-06-18\_PD51-Collaboration%20Meeting-ZhouYi-Finel ndf

# Development of RWELL detectors for large area & high rate applications




https://indico.cern.ch/event/889369/contributions/4020068/attachments/ 2115585/3559626/RD51CollaborationMeeting-sgf.pdf


# **COMPASS RICH Upgrade: Hybrid THGEM + MM with Csl PC**

COMPASS RICH I: 8 MWPC

with CsI since 2000




MWPC's + Csl



MWPC+CSI:
successful but with
performance limitations
for central chambers

8 Years of Dedicated R&D: THGEM+ Csl

**New Hybrid THGEM + MM PDs:** 



#### **Production THGEM @ ELTOS Company:**



grain pumice powder, pressure water cleaning, ultrasonic Bath with Sonica PCB solution (PH11), distilled water rinsing and oven @ 160 °C Assembly of Hybrid THGEM +MM:




# **Simulation Tools and Modelling of MPGDs**


## MPGDs and the mean free path

- ➤ Recall:
  - Mean free path of electrons in Ar: 2.5 μm,
- Compare with:
  - Micromegas mesh pitch: 63.5 μm
  - ▶ GEM polyimide thickness: 50 μm
  - Micromegas wire thickness: 18 μm
  - GEM conductor thickness: 5 μm
- ► Hence:
  - mean free path approaches small structural elements;
  - such devices should be treated at a molecular level.
- ▶ In addition, MPGDs usually have structures for which no nearly-exact (e.g. 3d structures) fields are known.

Modelling and simulation are crucial for detailed understanding of detector physics and for developing and exploiting novel MPGD technologies


- Resistive detectors: modelling of signal induction, understand protection schemes and rate capabilities
- Ion physics: minimise ion backflow, understand ion-induced damages and feedback processes, ion species/clustering and mobility
- Modelling of scintillation processes for optical readout: light production, quenching, timing
  of light production processes






## Gas mixture studion

#### Gain simulations in MPGDs including space charge effect using Elmer




https://indico.cem.ch/event/889369/contributions/ 4039491/attachments/2115151/3558785/ APellecchia\_Elmer\_RD51\_Oct2020.pdf

# F impurities




#### ATLAS NSW Micromegas mesh transparency




F. Kuger et al., https://doi.org/10.1016/j.nima. 2015.11.011


#### A fast simulation method for THGEM charging-up study




https://indico.cem.ch/event/989298/contributions/4225007/attachment 2192182/3706373/Guofeng-202102-RD61.pdf


27













# ULTIMATE INTEGRATION OF GASEOUS and SIICON DETECTORS –

# PIXEL READOUT of MICRO-PATTERN GASEOUS DETECTORS







## Pixel Readout of MPGDs: "GridPix" Concept


"InGrid" Concept: By means of advanced wafer processing-technology INTEGRATE MICROMEGAS amplification grid directly on top of CMOS ("Timepix") ASIC


3D Gaseous Pixel Detector → 2D (pixel dimensions) x 1D (drift time)







19 21 SEI








high resistive material 15 μm aSi:H (~10<sup>11</sup> Ω·cm) 8 μm Si N (~10<sup>14</sup> Ω·cm)



X600





# **MPGD-Based Gaseous Photomultipliers**


GEM or THGEM Gaseous Photomultipliers (CsI -PC) to detect single photoelectrons

# Multi-GEM (THGEM) Gaseous Photomultipliers:

- ✓ Largely reduced photon feedback (can operate in pure noble gas & CF₄)
- √ Fast signals [ns] → good timing
- √ Excellent localization response
- √ Able to operate at cryogenic T











# **Summary & conclusion**

Christian Lippmann, 2<sup>nd</sup> ECFA High Luminosity LHC Experiments Workshop, Aix-les-bains, France, October 21-23 (2014)

Geiger- Müller (1908), 1928 Drift Tube (1968) G. Charpak, 1968 Multi Wire Proportional Chamber R. Santonico, 1980 Resistive Plate Chamber




4)




3)

... will at HL-LHC be joined by:

F. Sauli (1997)
Gas Electron Multiplier



I. Giomataris et al. (1996) Micro-mesh gaseous chamber (Micromegas)





# **MPGD Technologies @ CERN Experiments**

 The integration of MPGDs in large experiments was not rapid, despite of the first large-scale application in COMPASS at SPS in the 2000's

- Scaling up MPGD detectors, while preserving the typical properties of small prototypes, allowed their use in the LHC upgrades
  - → Many emerged from the R&D studies within the CERN-RD51 Collaboration

Experiment / Timescale	Application Domain	MPGD Technology	Total detector size / Single module size	Operation Characteristics / Performance	Special Requirements / Remarks
COMPASS TRACKING > 2002	Fixed Target Experiment (Tracking)	3-GEM Micromegas w/ GEM preampl.	Total area: 2.6 m <sup>2</sup> Single unit detect: 0.31x0.31 m <sup>2</sup> Total area: ~ 2 m <sup>2</sup> Single unit detect: 0.4x0.4 m <sup>2</sup>	Max.rate: ~100kHz/mm² Spatial res.: ~70-100µm (strip), ~120µm (pixel) Time res.: ~ 8 ns Rad. Hard.: 2500 mC/cm²	Required beam tracking (pixelized central / beam area)
TOTEM TRACKING: > 2009	Hadron Collider / Forward Physics (5.3≤ η  ≤ 6.5)	3-GEM (semicircular shape)	Total area: ~ 4 m²  Single unit detect: up to 0.03m²	Max.rate:20 kHz/cm <sup>2</sup> Spatial res.: ~120μm Time res.: ~12 ns Rad. Hard.: ~ mC/cm <sup>2</sup>	Operation in pp, pA and AA collisions.
LHCb MUON DETECTOR > 2010	Hadron Collider / B-physics (triggering)	3-GEM	Total area: ~ 0.6 m <sup>2</sup> Single unit detect: 20-24 cm <sup>2</sup>	Max.rate:500 kHz/cm² Spatial res.: ~ cm Time res.: ~ 3 ns Rad. Hard.: ~ C/cm²	Redundant triggering
COMPASS RICH UPGRADE > 2016	Fixed Target Experiment (RICH - detection of single VUV photons)	Hybrid (THGEM + Csl and MM)	Total area: ~ 1.4 m <sup>2</sup> Single unit detect: ~ 0.6 x 0.6 m <sup>2</sup>	Max.rate:100 Hz/cm <sup>2</sup> Spatial res.: <~ 2.5 mm Time res.: ~ 10 ns	Production of large area THGEM of sufficient quality
ATLAS MUON UPGRADE CERN LS2	Hadron Collider (Tracking/Triggering)	Resistive Micromegas	Total area: 1200 m <sup>2</sup> Single unit detect: (2.2x1.4m <sup>2</sup> ) ~ 2-3 m <sup>2</sup>	Max. rate:15 kHz/cm² Spatial res.: <100µm Time res.: ~ 10 ns Rad. Hard.: ~ 0.5C/cm²	Redundant tracking and triggering; Challenging constr. in mechanical precision
CMS MUON UPGRADE CERN LS2	Hadron Collider (Tracking/Triggering)	3-GEM	Total area: ~ 143 m² Single unit detect: 0.3-0.4m²	Max. rate:10 kHz/cm <sup>2</sup> Spatial res.: ~100μm Time res.: ~5-7 ns Rad. Hard.: ~0.5 C/cm <sup>2</sup>	Redundant tracking and triggering
ALICE TPC UPGRADE CERN LS2	Heavy-Ion Physics (Tracking + dE/dx)	4-GEM / TPC	Total area: ~ 32 m <sup>2</sup> Single unit detect: up to 0.3m <sup>2</sup>	Max.rate:100 kHz/cm <sup>2</sup> Spatial res.: ~300μm Time res.: ~ 100 ns dE/dx: 11 % Rad. Hard.: 50 mC/cm <sup>2</sup>	- 50 kHz Pb-Pb rate; - Continues TPC readout - Low IBF and good energy resolution





# **CERN Detector Seminars in 2022: LS2 Upgrades**

Major MPGDs developments for ATLAS, CMS, ALICE upgrades, towards <u>establishing</u> <u>technology goals</u> and technical requirements, and <u>addressing engineering and integration</u> <u>challenges</u> ... and first results from Run 3!!!

"The New Small Wheel project of ATLAS" by Theodoros Vafeiadis (17 Jun 2022)


https://indico.cern.ch/event/1168778/


# "Continuous data taking with the upgraded ALICE GEM-TPC"


by Robert Helmut Munzer (24 Jun 2022), https://indico.cern.ch/event/1172978/

"The GEM detectors within the CMS Experiment" Michele Bianco (08 Jul 2022) https://indico.cern.ch/event/1175363/

All three major LHC upgrades, incorporating MPGDs, started their R&D in close contact with RD51, using dedicated setups at GDD-RD51 Laboratory








# Large-Area MM / GEM Detectors for ATLAS / CMS Upgrade

#### **Resistive MM for ATLAS NSW Muon Upgrade:**

Standard Bulk MM suffers from limited efficiency at high rates due to discharges induced dead time Solution: Resistive Micromegas technology

- Add a layer of resistive strips above the readout strips
- Spark neutralization/suppression (sparks still occur, but become inoffensive)



#### Still, main issue encountered: HV unstability

==> found to be correlated to low resistance of resistive strip anode ==> applied solutions + passivation in order to deactivate the region where R<0.8  $M\Omega$ 

#### **Production, sector integration (~1200m² resistive MM):**






#### **GEMs for CMS Muon System Upgrade:**

Single-mask GEM technology (instead of double-mask)
 Reduces cost /allows production of large-area GEM



→ Assembly optimization: self-stretching technique:
 → assembly time reduction to 1 day






September 2020: 144 GEM chambers installed




# TPC with MPGD Readout for ALICE Upgrade and ILC

ALICE TPC → replace MWPC with 4-GEM staggered holes (to limit space-charge effects)



- Upgrade for continuous
   TPC readout @ 50 kHz
   Pb-Pb collisions
- Phys. requirements: IBF < 1%, Energy res. σ(E)E < 12%

TPC reinstallation in the ALICE cavern (August 2020)







#### **ILC -TPC with MPGD-based Readout**

Target requirement of a spatial resolution of 100 um in transverse plane and dE/dx resolution < 5% have been reached with all technologies (GEM, MM and GridPix)


If dE/dx combined with ToF using SiECAL,
P < 10GeV region for pion-K separation covered






#### ILC: gating scheme, based on large-aperture GEM

- Machine-induced background and ions from gas amplific.
- → Exploit ILC bunch structure (gate opens 50 us before the first bunch and closes 50 us after the last bunch)





# **Towards Large-Scale Pixel "GridPix" TPC**

Testbeams with GridPixes:

160 GridPixes (Timepix) & 32 GridPixes (Timepix3)



# A PIXEL TPC IS REALISTIC!



3 modules for LP TPC @ DESY: 160 (1 x 96 & 2 x 32) GridPixs 320 cm<sup>2</sup> active area, 10,5 M. channels, new SRS Readout system





#### **Physics properties of pixel TPC:**

- Improved dE/dx by cluster counting
- Improved meas.of low angle tracks
- Excellent double track seperation
- Lower occupancy @ high rates
- Fully digital read out (TOT)

#### Quad board (Timepix3) as a building block

→8-quad detector (32 GridpPixs) with a field cage at test-beam @DESY in June 2021:





- ion back flow can be further reduced by applying a double grid.
- Protection layer resistivity to be reduced
- New Timepix4 developments

## Dissemination of MPGD Applications in HEP & Other Fields

SPRINGER NATURE Reference

han 20th do Thu

(No Mark

Not > 3(3)

Nath State

Sur - 309

Rev 2005 new

Horn-ker/hours

(Tracking - 40 life)

Marrippin

Ivor Fleck Maxim Titov Claus Grupen Irène Buvat Editors

# Handbook of Particle Detection and Imaging

<u>Springer</u>

#### Gaseous Detectors

Maxim Titov

#### Contents


Contents	
Introduction.	
Basic Principles: Ionization, Transport Phenomena and Avalanche Multiplication	
The Multi-Wire Proportional, Drift, and Time Projection Chambers.	
Micro-Pattern Gaseous Detectors.	
Micro-Pattern Gaseous Detector Applications.	2
Overview of the CERN-RD51 Collaboration	
Future R&D Program for Advanced MPGD Concepts	
Summary and Outlook.	3
Cross-References	
Bibliography	3

#### Abstract

Over the course of the last 50 years, the advances and breakthrough in instrumentation, leading to the development of new, cutting-edge technologies, drove the progress in experimental particle physics. A true innovation in detector concepts came in 1968, with the development of a fully parallel readout for a large array of sensing elements – the Multi-Wire Proportional Chamber (MWPC), which carned Georges Charpak a Nobel Prize in Physics in 1992. This invention revolutionized particle detection, which moved from optical-readout devices (cloud chamber, emulsion or bubble chambers) to the electronics era. Since then, radiation detection and imaging with gaseous detectors, capable of economically covering large detection volume with low mass budget, have been playing an important role in many fields of science. Over the past three decades, advances in photo-lithography, microelectronics, and printed-circuit bard (PCB) techniques

#### MPGD Technologies for the International Linear Collider

Esperiment/ Timecale	Application Domain	MPGD Indusings	Total detector size / Single module size	Operation Characteristics? Performance	Special Requirements Remarks
EC Tour Projection Charter for EU Seat. + 200	High Every Dysics (making)	Microspe CDE guild SeCol (parts)	Total anni - 20 m <sup>2</sup> Single unit direct - 400 cm <sup>2</sup> (publi - 120 cm <sup>2</sup> (publi	Macade (10%) Speldine: (25m Tone out - 25m dicks 5% (abh) Rad Rad, no	S - DC Manuscan modules: dpg - PSS I MaY fover publing
OCHalmer (DICAL) Calminety in EDSD Surt > 200	High Energy Physics (colonology)	CINC TRCINI BPASSI, Mananagan	September September 15-1 of	Macain Tallaton' Spatial ext Icm Time exc Time Ead Hard: no	Jeforgy malation 34% Prescripting sel- trigging malast



#### MPGD Tracking Concepts for Hadron / Nuclear Physics

Experiment/ Timescale	Application Domain	MPCD Sockerlage	Total detector size / Single module size	Operation Characteristics' Performance	Special Exquirements/ Ecnarko
COMPAN & CON See 202-new	Slabor Physics (Tracking)	CDN Museeque n' CDN prompt	Sedant Seri Sejo uto Seun ESIASSEr Sedant - Sejo uto deut Sejo uto deut Saldar	Macon IPTIs s IRRitano*; spelator: Tritisa torp: -Daniposi Tieres: -to Eat Rad: DitroCos*	Registed beam tracking (student) correct beam area)
Ber 200 nov	Percisity (Trakey)	COM .	findam dist	Macsale (Nitrino) Spatial rec - Tipm	
Sun-207	Nulse Physics (Socking) authorities Scientimen	CON	Total and 18 of Single-unit direct (18 of Seri	Mes not diffations' Spatial not: "Type Time not: - () for Each florid (C) ()	
Nat 207	Nuclear Physics (Tooking) precision beau of proton cubus	CON	Total over 1 for Single-unit direct 12 (1 m 2	Max sea Folician' Spatial ass. Olive Time ass Olive Ked Hard: 174Cyy	
Sun -> 201	Notice Physics (Itacking)	covi	Trial and little' Single-wit direct 120 mil 2	Macane officialism Spatial no Office Timenty - Office Bad Mad CO-Lidge	
Fill and Edit offices: Next -2020	Sales Syste (Society)	DE HIGHE peoples	Sind and Eller' EStrollament at Smiller length	Maces If Viscol Spalding (24) inco	Georgial operate-100
ACMETIC Sun-SOllarity	Nuclear physics Nuclear resultant Basilian processes	TIC sc Mannings (any pay-10) unit	Tawter 292 inched IIPSet	Cruming sale-37 Shadel but higher of annu-beam moles propered.	Wed with nations gar (file extenses, ICBOLTC)

#### Cylindrical MPGDs as Inner Trackers for Particle / Nuclear Physics

Bellew To

Marioty DNISt or

Rad Hard: 199Cir

初かけいかち

States 1989' Marie 1980co' to NYChannel Installed 1980 Are III migni

Special Control	Application Demand	MPLD Technology	Inchance do: Negle mode on	Openior Characterists Technology	Special Engineerate Entable
GENERALINE No. 204207	Parkir Physics E-Save physics (Dasking)	Colonial COM		Spelatery (to-20cm Spelately-20cm	-Mat hutget 2's N -Operation in 63's
MINI Uppud-1 Rejinj Res 205-202	Funda Physiol ere collabe (Toolog)	Opening CDI	Toledraliem E-2ion	Ma, sec (Hallycon) Spatial except - Olivin Spatial except - I min	-Manual 1175 of X, for all layers -Operator in 17
Sun > 207	Nulse Resor Nulses encluse (couling)	Plane Several A Cylindrical States) Manager	Tenlane Served - bian' Barel - 37m' Diplomatiques E - 25 m	Macrate - 37500 Spelafrac - 27500 Time may 2750	- Low material budget (14% NO - Remote discussion
MARCON OCURN But 2014 - new	Nation Physis Cracking and verticing of presimating from the purely weekfallers	Olehed Manega-20	2-pfedoul layers L-silvan B-45-Mass	Mactigenerids Spirites: 20pe Secret: the Set Red./Conf	Carp majoris fall that rates from its Clin de activares
MNON Nex 2014-2014	Noterous	Hongs Mongo	Lighted light Liftigs, R-18cm	Spelates chan FWIM Sign on spin-CESs	-Cormond Sulpt
OND FUggale # NOT Name - 2007	Tarsity/fesix (s-dueler, tecking)	CENE	Total asser - No. 2 plindical layers	Spelation: 100cm	

#### MPGD Tracking for Heavy Ion / Nuclear Physics

Esperiment/ Especiale	Application Districts	MPGD Solveings	Total detector size? Single mobile size	Operation Characteristics/ Ferformance	Special Requiremental Remarks
Dates BIC Sates BIC No. 202 poses	New Jor Physics (making)	CIM	Induse-Tori Segleumbeut -Oaklay'	Spatial on, 10 (10 pm.	Les mand halps: +75 Mys malogioss
National Mark UNIXATIVE Start > 2027	Skey less Papes (recking)	OM	Snalunu - Cof Single and Ameri - 6 Fe/	Macone-101Mile Speliation: 20lan	Majoric feld 175 orthografi selects Md
Ser 2012/2	Swep in Physics tracking Supression of the let the Supression Engineer Supression	DC+i CIM	Sealure for of Single and Amer Sign E. No Scott Sign E. No Scott	Macon-IPTOspit Spatialists into	High dynamic nery Particle detection from you'll remove
PANDA HEAR National	Nuterphysis p-ant-thicking	OM:	Stalana - Stal Sinjir unit desct - 13 m²	Max set = 14M/3000* Spatial max = 27000	Centrume von operative. 37' stencismit.
CM 4 (ASE Not - 30)	Nuclear Physics (Marth Aprill)	COM	Single and American Electronic American	Spelial eq. ( ) ten Max rate ( ) Milholor Famo eq. ( ) fine Suit hard. (0)* ( ) ( ) ( ) ( )	Metged detres
Demoke Orbitr(DC) Swt,+203	Sales Physic (trading \$125)	TPC viCEM realized Large sear-CEM planer tracking detectors	Total anni - Terl Total anni - 27 mil	Spelializer, 1974 pt. Lamberty (r.y.), 32° Spelializer, 1974 (films), Marches, 1974 (r.y.)	
Marian Sil	Wall Wall	W. Z.	NI S	200	_ bail-

#### MPGD Technologies for Photon Detection

Experiment/ Expecials	Application Domain	MPCD Sechoology	Total detector size / Single andele size	Operation Characteristics / Performance	Special Requirements/ Remarks
COMPANIED I	Halon Physics (IDCH-detection of single VLV photons)	(BIGSN-CA (BIGSN-CA and NO)	Index-Lin' Segirations, -bis (Se)	Macan William Spale oc - 22 am Fine oc - 17 m	Production of large and TREAM of multi-large quality
PHENDORD Res 209-200	Nuclear Physics (8001 - arb repression)	GEN-Cd dentes	Trislanc - 12m <sup>2</sup> Segleunt Anno - 03x53m <sup>2</sup>	No. sec in Spild so Tracing Sign of ell NYS	Single of, eff, depends from Nadion sejection factor
998NN Res 200-200	Steep landbysis (tracking)	TPC+CEM	Testanc-Tel	Multipliety 2NASty - 600 Spelid Inc 200 un (16)	Not with livery law and companion tryp operation
Distrocke Unlike (UC) Statt > 203	Salor/Spics (racking 800)	TPC+/CEM medical- Chemism	Intanchal	Speldon: - Offen op Lamboully (n.g.) 20°	Live moterial holger
		BOI viti.	Total area - 18 m²	Spild so: in on	Hyb single decision adkins cy








https://indico.cern.ch/event/581417/contributions/2558346/attachments/1465881/2266161/2017\_05\_Philadelphia \_\_MPGD2017-ConferenceSummary\_25052017\_MS.pdf

## **MPGD Technologies @ Future R&D Trends**


 <u>RESISTIVE MATERIALS</u> and related detector architectures for single-stage designs (μPIC, μ-RWELL, RPWELL, resistive MM)

→ improves detector stability; single-stage is advantage for assembly, mass production & cost.




Diamond-like carbon (DLC) resistive layers

→ Solutions to improve high-rate capability (≥ MHz)



Picosecond Timing Detector (RD51 PICOSEC Collaboration) – MM device with radiator and radiation-hard PC

OPTICAL READOUT: hybrid approaches combining gaseous with non-gaseous in a single device (e.g. CYGNUS- TPC project):




New manufacturing techniques & structures:

- Solid-state photon and neutron converters,
   <u>INNOVATIVE NANOTECHNOLOGY</u>
   <u>COMPONENTS (graphene layers);</u>
- Material studies (low out-gassing, radiation hardness, radio-purity, converter robustness and eco-friendly gases.
- Emerging technologies related to novel PCs, MicroElectroMechanical Systems (MEMS), sputtering, 3-D printing of amplifying structures and cooling circuits

# **Advanced Concepts Picosecond (a few 10's) Timing Detectors**

Several types of technologies are considered for "Picosecond-Timing Frontier":

- lonization detectors (silicon detectors or gas-based devices)
- Light-based devices (scintillating crystals coupled to SiPMs, Cherenkov absorbers coupled to photodetectors with amplification, or vacuum devices)



# **Towards Large Area in Fast Timing GASEOUS DETECTORS**

#### Multi-Gap Resistive Plate Chambers (MRPC):



✓ New studies with MRPC with 20 gas gaps using a low-resistivity 400 µm-thick glass → down to 20 ps time resolution





Fig. 1. Cross section of the double stack 20-gap MRPC.




Stack of equally-spaced resistive plates with voltage applied to external surfaces (all internal plates electrically floating)

Pickup electrodes on external surfaces - ( any movement of charge in any gap induces signal on external pickup strips)

Internal plates take correct
voltage - initially due to
electrostatics but kept at
correct voltage by flow of
electrons and positive ions feedback principle that dictates
equal gain in all gas gaps

Micromegas


#### Gaseous Detectors: Micromegas with Timing (RD51 Picosec Collaboration)



σ ~ 25 ps timing resolution (per track)

Cherenkov radiator + Photocathode + Micromegas





Signal electrode

Cathode -10 kV

Single pad (2016)

10x10 module

https://indico.cern.ch/event/1040998/contributions/4398412/ attachments/2265036/3845651/PICOSEC-update-final.pdf

25

## Optical Readout for Micro-Pattern Gaseous Detectors


**Courtesy CERN GDD group** 

#### Concept


Scintillation light emitted during amplification processes in MPGDs can be read out with CCD or CMOS cameras.

GEM readout

Glass Micromegas readout




Emission spectrum of Ar / CF4 gas mixture with UV and visible scintillation




#### **Examples and applications**

X-ray radiography


Energy-resolved imaging






Track reconstruction

Beam monitoring





Rapid X-ray imaging (fluoroscopy) with sub-ms exposure per frame












#### **R&D** and current projects

Low-pressure optical TPC to resolve events with wide dynamic range (low energy X-rays in presence of alpha particle or nuclear recoils)



Use of high-speed cameras for 3D track reconstruction resolving drift time differences












## The CYGNO TPC: Optical Readout for Directional Study of Rare Events


CYGNO is working in the framework of CYGNUS: international Collaboration for realization of Multi-side Recoil Directional Observatory for WIMPs &  $\nu$ 's

PHASE 0: R&D PHASE 1: ~1 m<sup>3</sup> Demonstrator 2015/16 2017/18 2019/20 2021/22 2023 @ LNF @ ROMA1 @ LNF/LNGS @ LNF/LNGS @ LNGS LIME **ORANGE** LEMON Construction Installation & & test commissioning SYGNUS - 3D printing - 1 cm drift 50 cm drift - 20 cm drift underground tests shielding - background materials test - gas purification - scalability **CYGNUS RD - CSN5** CYGNO - CSN2

GEM Optical readout: Promising performance in a few keV region



A sizeable efficiency in the range 5-10 keV was measured while more than 95% (99%) 55Fe photons were rejected



Optically readout TPC: 3D tracking (position and direction); total released energy measurement and dE/dx profile;

## 1M3 DEMONSTRATOR: BASELINE LAYOUT

1 m<sup>3</sup> of He/CF<sub>4</sub> 60/40 (1.6 kg) at atmospheric pressure with a composed by two 50 cm long TPC with a central cathode and a drift field of about 1 kV/cm;

Acrylic vessel ensuring gas tightness and high voltage insulation;

lunta sin East 133

Each side equipped by a 3x3 matrix of LIME-like:

sCMOS sensor 65 cm

Almost 108 readout pixels 165 x 165  $\mu$ m<sup>2</sup>

Fast light detector (PMT or SiPM).

Radioactivity shielding:

- 5 cm thick copper box (Faraday cage too);
- 200 cm of water.

# Graphene-based Functional Structures and Nanostructures for novel MPGD Concepts


Graphene layers for. ion-backflow suppression, protection of photocathodes, solid conversion layers


PhD project of Giorgio Orlandini (FAU Erlangen-Nürnberg) in EP-DT-DD Gaseous Detector Development lab

The unique properties of two-dimensional materials such as graphene as well as carbon-based nanostructures offer new perspectives for novel gaseous radiation detectors. This may include performance improvements for detectors for HEP experiments as well as new application fields combining wideband sensitivity of advanced materials with high gain factors and granularity offered by Micro Pattern Gaseous Detectors.

#### Application 1:

Suspended graphene for ion backflow suppression and gas separation






Suppressing ion back flow can significantly improve high-rate capabilities and reduced electric field distortions in Time Projection Chambers.

#### Application 2:

Protection of photocathodes with graphene layers




s41699-018-0062-6

Atomically thin coating layers could protect sensitive photocathodes such as CsI against environmental factors and ion bombardment, which is important for preserving specifications of precise timing detector in harsh ion-back flow conditions. Additionally, modifications of the work functions of converter layers can be used to increase QE.

#### Application 3:

Graphene and nanostructures for photoconversion and as solid converters



Graphene quantum dots (GQD), carbon nanotubes and graphene have been shown to exhibit broadband sensitivity and could be used as versatile conversion layers. Utilising solid conversion layers enables high detection efficiencies and can be used for precise timing with gaseous radiation detectors.



Knowledge is limited. Whereas the Imagination embraces the entire world... Albert Einstein

Bridge the gap between science and society ...

# The Role of Big High Energy Physics Laboratories: - innovate, discover, publish, share




... and bring the world closer together




# Scintillating GEM for Dose Imaging in Radiotherapy

Scintillation Light (Optical) & Charge Readout:




#### Light output for 138 MeV protons:

Scintillation type	Gas gain	Light signal (CCD) at 1Gy proton dose (ADU)
Screen (Gd <sub>2</sub> O <sub>2</sub> S:Tb)		2670
Ar/CO <sub>2</sub> (90:10)	3000	270
Ar/CF <sub>4</sub> (90:10)	1400	2350
Ar/CF <sub>4</sub> (95:5)	1300	4000
Ar/CF <sub>4</sub> (97,5:2,5)	770	2000



#### LIGHT SIGNAL FROM GEM:

(only 4% smaller than ionization chamber signal)




## **NEWS-G: Search for Dark Matter with Spherical Proportional Counters**


**NEWS-G Collaboration:** 5 countries, 10 institutes, ~40 collaborators


#### Three underground laboratories:

- ✓ SNOLAB
- √ Laboratoire Souterrain de Modane
- ✓ Boulby Underground Laboratory




# Nuclear Quenching Factor measurements:





#### The Spherical Proportional Counter




#### Basic advantages

- Large volume/ few read-out channels
- Single electron threshold:
  - Low capacitance
  - High gain
- Radio-pure construction
- Background rejection handles
- Flexible operation
  - Swappable gases-targets
  - Variable pressure choice

#### **Increasing Target Mass and Reducing Background:**

- ACHINOS, electroformation, ...
- ✓ Several detectors scheduled for the coming years
- Eventually sensitivity could reach neutrino floor



# CEVNS & NEWS-G

#### CEVNS opens a window to investigation non-standard neutrino interactions

- ▶ First observations by COHERENT in NaI (2017) and Ar (2020)
- ▶ Unique complementarity with DM searches as sensitivity reaches the neutrino floor
- NEWS-G3: A low-threshold low-background sea-level facility
- Environmental and cosmogenic background studies towards reactor CEvNS studies
- ▶ Shielding: Layers of pure copper, polyethylene, and lead, with active muon veto
- Commissioning in 2021